

R&S® CMW500

Wideband Radio

Communication Tester

Specifications



CONTENTS

General technical specifications	8
RF generator.....	8
<i>Modulation source: arbitrary waveform generator (ARB) (R&S®CMW-B110A/R&S®CMW-B110D option)</i>	<i>10</i>
RF analyzer.....	10
<i>Power meter</i>	<i>11</i>
<i>Spectrum measurements</i>	<i>12</i>
Possible configurations with two RF paths	14
<i>Configuration with two H570 (RF TRX) and two H590A (RF frontend (BASIC)).....</i>	<i>14</i>
<i>Configuration with two H570 (RF TRX) and one H590D (RF frontend (ADV.))</i>	<i>14</i>
Possible configurations with four RF paths	15
<i>Configuration with two H570 (RF TRX), two H571B (RF TX) and two H590D (RF frontend (ADV.))</i>	<i>15</i>
<i>Configuration with four H570 (RF TRX) and two H590D (RF frontend (ADV.))</i>	<i>16</i>
Timebase	18
<i>Timebase TCXO.....</i>	<i>18</i>
<i>Timebase basic OCXO (R&S®CMW-B690A option)</i>	<i>18</i>
<i>Timebase highly stable OCXO (R&S®CMW-B690B option).....</i>	<i>18</i>
<i>Reference frequency inputs/outputs.....</i>	<i>18</i>
Audio specifications (prerequisite: R&S®CMW-B400B)	19
Audio analyzer	19
<i>Statistics</i>	<i>19</i>
<i>Audio filter, weighting</i>	<i>19</i>
<i>Connectors AF 1 IN / AF 2 IN.....</i>	<i>19</i>
<i>AF voltmeter</i>	<i>19</i>
<i>THD+N and THD meter.....</i>	<i>19</i>
Audio generator	19
<i>Connectors AF 1 OUT / AF 2 OUT.....</i>	<i>19</i>
<i>AF sine generator.....</i>	<i>19</i>
Digital interface unbalanced.....	20
<i>BNC rear panel connectors</i>	<i>20</i>
GSM specifications – mobile station test	21
GSM RF generator (prerequisite: R&S®CMW-B110A/R&S®CMW-B110D option)	21
<i>GSM GEN (R&S®CMW-KG200 option).....</i>	<i>21</i>
<i>GSM WinIQSIM2™ (R&S®CMW-KW200 option), GSM EDGE EVO WinIQSIM2™ (R&S®CMW-KW201 option).....</i>	<i>21</i>
GSM RF analyzer (R&S®CMW-KM200 option) and GSM EDGE EVO A analyzer (R&S®CMW-KM201 option).....	22
<i>Modulation analysis.....</i>	<i>22</i>
<i>Power versus time measurement.....</i>	<i>23</i>
<i>Spectrum due to modulation measurement</i>	<i>23</i>
<i>Spectrum due to switching measurement</i>	<i>23</i>
GSM signaling (prerequisite: R&S®CMW-KS200, R&S®CMW-KS201, R&S®CMW-KS203, R&S®CMW-B200A, R&S®CMW-B210A options; additionally R&S®CMW-KS210 option and R&S®CMW-KS211)	23

WCDMA specifications – mobile station (UE) test	24
WCDMA RF generator (prerequisite: R&S®CMW-B110A/R&S®CMW-B110D option)	24
<i>WCDMA GEN (R&S®CMW-KG400 option), WCDMA HSPA GEN (R&S®CMW-KG401 option).....</i>	<i>24</i>
<i>WCDMA WinIQSIM2™ (R&S®CMW-KW400 option), WCDMA HSDPA WinIQSIM2™ (R&S®CMW-KW401 option),</i>	
<i>WCDMA HSUPA WinIQSIM2™ (R&S®CMW-KW402 option), WCDMA HSPA+ WinIQSIM2™ (R&S®CMW-KW403 option)</i>	<i>24</i>
WCDMA RF analyzer (R&S®CMW-KM400, R&S®CMW-KM401, R&S®CMW-KM403 options).....	25
<i>Modulation analysis.....</i>	<i>25</i>
<i>Spectrum measurements</i>	<i>26</i>
<i>Power meter</i>	<i>26</i>
3G WCDMA signaling (prerequisite: R&S®CMW-KS400, R&S®CMW-B300A/R&S®CMW-B300B options; additionally R&S®CMW-KS410 and R&S®CMW-KS425 option).....	27
LTE specifications – mobile station test	28
LTE RF generator (prerequisite: R&S®CMW-B110A/R&S®CMW-B110D option).....	28
<i>LTE WinIQSIM2™ (R&S®CMW-KW500 option).....</i>	<i>29</i>
LTE FDD RF analyzer (R&S®CMW-KM500 option).....	29
<i>Power measurement</i>	<i>30</i>
<i>Modulation analysis.....</i>	<i>30</i>
<i>Spectrum measurements</i>	<i>31</i>
LTE FDD eNodeB RF analyzer (R&S®CMW-KN500 option).....	31
<i>Power measurement</i>	<i>32</i>
<i>Modulation analysis.....</i>	<i>32</i>
<i>Spectrum measurements</i>	<i>32</i>
LTE FDD signaling (prerequisite: R&S®CMW-KS500, R&S®CMW-B300A/R&S®CMW-B300B options)	33
<i>DL signal</i>	<i>33</i>
LTE TDD RF analyzer (R&S®CMW-KM550 option).....	34
<i>Power measurement</i>	<i>34</i>
<i>Modulation analysis.....</i>	<i>34</i>
<i>Spectrum measurements</i>	<i>35</i>
LTE TDD eNodeB RF analyzer (R&S®CMW-KN550 option)	36
<i>Power measurement</i>	<i>36</i>
<i>Modulation analysis.....</i>	<i>36</i>
<i>Spectrum measurements</i>	<i>37</i>
Bluetooth® specifications.....	38
Bluetooth® RF generator (prerequisite: R&S®CMW-B110A/R&S®CMW-B110D option).....	38
<i>Bluetooth® WinIQSIM2™ (R&S®CMW-KW610 option)</i>	<i>38</i>
Bluetooth® RF analyzer (R&S®CMW-KM610 option).....	38
<i>Modulation analysis.....</i>	<i>39</i>
Bluetooth® signaling (prerequisite: R&S®CMW-KS600, R&S®CMW-KS610).....	40
Bluetooth® RF analyzer (R&S®CMW-KM611 option).....	41
<i>Modulation analysis.....</i>	<i>41</i>

GPS specifications	42
GPS RF generator (prerequisite: R&S®CMW-B110A/R&S®CMW-B110D option).....	42
<i>GPS WinIQSIM2™ (R&S®CMW-KW620 option)</i>	42
DVB specifications	42
DVB RF generator (prerequisite: R&S®CMW-B110A/R&S®CMW-B110D option).....	42
<i>DVB WinIQSIM2™ (R&S®CMW-KW630 option)</i>	42
FM STEREO RADIO specifications	43
FM STEREO RADIO generator (prerequisite: R&S®CMW-B110A/R&S®CMW-B110D option).....	43
<i>FM STEREO RADIO waveforms (R&S®CMW-KV645 option)</i>	43
FM STEREO RADIO analyzer (R&S®CMW-KM645 option).....	43
<i>Audio filter, weighting</i>	43
<i>RF carrier analysis</i>	43
<i>Modulation analysis</i>	43
WLAN specifications	44
WLAN RF generator (prerequisite: R&S®CMW-B110A/R&S®CMW-B110D option).....	44
<i>WLAN ABG WinIQSIM2™ (R&S®CMW-KW650 option)</i>	44
<i>WLAN N WinIQSIM2™ (R&S®CMW-KW651 option)</i>	45
<i>WLAN AC WinIQSIM2™ (R&S®CMW-KW656 option)</i>	45
WLAN ABG RF analyzer (R&S®CMW-KM650 option).....	45
<i>Modulation analysis</i>	46
<i>Spectrum measurements</i>	47
WLAN N RF analyzer (R&S®CMW-KM651 option).....	47
<i>Modulation analysis</i>	47
<i>Spectrum measurements</i>	48
WLAN N MISO RF analyzer (R&S®CMW-KM652 option).....	49
<i>Modulation analysis</i>	49
WLAN N switched MIMO RF analyzer (R&S®CMW-KM653 option).....	50
<i>Modulation analysis</i>	50
WLAN P RF analyzer (R&S®CMW-KM655 option).....	50
<i>Modulation analysis</i>	51
<i>Spectrum measurements</i>	52
WLAN AC RF analyzer (R&S®CMW-KM656 option).....	52
<i>Modulation analysis</i>	52
<i>Spectrum measurements</i>	53
WLAN signaling access point emulator (prerequisite: R&S®CMW-KS650, R&S®CMW-KS651, R&S®CMW-B200A, R&S®CMW-B270A options).....	53
<i>Physical layer OFDM</i>	54
<i>Measurements</i>	54
<i>Features</i>	54

WiMAX™ specifications – mobile station and base station test	55
WiMAX™ RF generator (prerequisite: R&S®CMW-B110A/R&S®CMW-B110D option).....	55
<i>WiMAX™ WinIQSIM2™ (R&S®CMW-KW700 option)</i>	<i>55</i>
WiMAX™ RF analyzer (R&S®CMW-KM700, R&S®CMW-KM701 options).....	55
<i>Power measurement</i>	<i>56</i>
<i>Modulation analysis.....</i>	<i>56</i>
<i>Spectrum measurements</i>	<i>57</i>
WiMAX™ signaling base station emulator (SISO prerequisite: R&S®CMW-KS700, R&S®CMW-B200A, R&S®CMW-B270A options, MIMO prerequisite: R&S®CMW-KS700, R&S®CMW-KS701, R&S®CMW-KS702, R&S®CMW-B200A, R&S®CMW-B270A options) ..	57
<i>Physical layer</i>	<i>58</i>
<i>Measurements.....</i>	<i>58</i>
<i>Features</i>	<i>59</i>
WiMAX™ IP application enabler (prerequisite: R&S®CMW-KA700, R&S®CMW-B660, R&S®CMW-B661 options).....	59
TD-SCDMA specifications – mobile station (UE) test	60
TD-SCDMA RF generator (prerequisite: R&S®CMW-B110A/R&S®CMW-B110D option)	60
<i>TD-SCDMA WinIQSIM2™ (R&S®CMW-KW750 option) and TD-SCDMA ENH. WinIQSIM2™ (R&S®CMW-KW751 option)</i>	<i>60</i>
TD-SCDMA RF analyzer (R&S®CMW-KM750 option).....	60
<i>Modulation analysis.....</i>	<i>61</i>
<i>Code domain</i>	<i>61</i>
<i>Spectrum measurements</i>	<i>61</i>
<i>Power meter</i>	<i>62</i>
TD-SCDMA signaling (prerequisite: R&S®CMW-KS750, R&S®CMW-B300A/R&S®CMW-B300B options).....	62
CDMA2000® 1xRTT specifications – mobile station test	63
CDMA2000® 1xRTT RF generator (prerequisite: R&S®CMW-B110A/R&S®CMW-B110D option)	63
<i>CDMA2000® GEN (R&S®CMW-KG800 option).....</i>	<i>63</i>
<i>CDMA2000® WinIQSIM2™ (R&S®CMW-KW800 option).....</i>	<i>63</i>
CDMA2000® RF analyzer (R&S®CMW-KM800 option)	64
<i>Modulation analysis.....</i>	<i>64</i>
<i>Code domain</i>	<i>65</i>
<i>Spectrum measurements</i>	<i>65</i>
<i>Power meter.....</i>	<i>65</i>
CDMA2000® 1xRTT signaling (prerequisite: R&S®CMW-KS800, R&S®CMW-B200A, R&S®CMW-B220A options).....	66

CDMA2000® 1xEV-DO specifications – access terminal test	67
CDMA2000® 1xEV-DO RF generator (prerequisite: R&S®CMW-B110A/R&S®CMW-B110D option).....	67
1xEV-DO WinIQSIM2™ (R&S®CMW-KW880 option).....	67
CDMA2000® 1xEV-DO RF analyzer (R&S®CMW-KM880 option).....	67
Modulation analysis.....	68
Code domain.....	69
Spectrum measurements.....	69
Power meter.....	69
CDMA2000® 1xEV-DO signaling (prerequisite: R&S®CMW-KS880, R&S®CMW-KS881, R&S®CMW-B200A, R&S®CMW-B230A options).....	69
Data application unit (R&S®CMW-B450D option)	70
Data application.....	70
Enabling of IP data interface for IPV4 (R&S®CMW-KA100 option).....	70
Enabling of IP data interface for IPV6 (R&S®CMW-KA150 option).....	70
IP multimedia subsystem server (R&S®CMW-KAA20 option).....	70
Data application measurements (R&S®CMW-KM050 option).....	70
IP analysis (R&S®CMW-KM051 option).....	70
LAN DAU interface.....	70
Digital I/Q 1 to 4 (R&S®CMW-B510F option) and digital I/Q 5 to 8 (R&S®CMW-B520F option)	71
Digital I/Q interface.....	71
AUX interface.....	71
Included extras.....	71
General data	72
Ordering information	74
Recommended extras for manual operation.....	74
Recommended extras.....	74
Service options.....	75

Specifications apply under the following conditions:

Data valid for the R&S®CMW500, the R&S®CMW280 and the R&S®CMW270 unless otherwise stated.

Data without tolerance limits is not binding. Based on a 24-month calibration interval unless otherwise stated. At least 15 minutes warm-up time at ambient temperature, specified environmental conditions met, calibration cycle adhered to, and all internal automatic adjustments performed. Typical values are designated with the abbreviation "typ.". These values are verified during the final test but are not assured by Rohde & Schwarz. Nominal values are design parameters that are not assured by Rohde & Schwarz. These values are verified during product development but are not specifically tested during production.

In line with the 3GPP/3GPP2 standard, chip rates are specified in Mcps (million chips per second), whereas bit rates and symbol rates are specified in Mbps (million bits per second), kbps (thousand bits per second) or ksp/s (thousand symbols per second), and sample rates are specified in Msample/s (million samples per second). Mcps, kbps, ksp/s and Msample/s are not SI units.

During the production process, each instrument is calibrated in line with defined procedures. All measurement results, including measurement uncertainties of the calibration system, have to be within the published specification limits to release the individual instrument. The expanded measurement uncertainties of the calibration system used in the production process are determined with a coverage factor of $k = 2$ (normally approx. 95 % probability).

Parameters written in italics can be set directly on the tester.

CDMA2000® is a registered trademark of the Telecommunications Industry Association (TIA - USA).

"WiMAX Forum" is a registered trademark of the WiMAX Forum. "WiMAX", the WiMAX Forum logo, "WiMAX Forum Certified" and the WiMAX Forum Certified logo are trademarks of the WiMAX Forum.

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by Rohde & Schwarz is under license.

Data without tolerance limits is not binding.

General technical specifications

RF generator

Frequency range		70 MHz to 3300 MHz, up to 6000 MHz with the R&S®CMW-KB036 option
Frequency resolution		0.1 Hz
Frequency uncertainty		same as timebase + frequency resolution

Output level range		
RF1 COM, RF2 COM	70 MHz to 100 MHz	
	continuous wave (CW)	-130 dBm to -15 dBm
	peak envelope power (PEP)	up to -15 dBm
	overranging (PEP)	up to -10 dBm
	100 MHz to 3300 MHz	
	continuous wave (CW)	-130 dBm to -5 dBm
	peak envelope power (PEP)	up to -5 dBm
	overranging (PEP)	up to 0 dBm
	3300 MHz to 6000 MHz	
	continuous wave (CW)	-120 dBm to -15 dBm
	peak envelope power (PEP)	up to -15 dBm
	overranging (PEP)	up to -10 dBm
	maximum input DC level	0 V DC
RF1 OUT	70 MHz to 100 MHz	
	continuous wave (CW)	-120 dBm to -7 dBm
	peak envelope power (PEP)	up to -7 dBm
	overranging (PEP)	up to +3 dBm
	100 MHz to 3300 MHz	
	continuous wave (CW)	-120 dBm to +3 dBm
	peak envelope power (PEP)	up to +3 dBm
	overranging (PEP)	up to +13 dBm
	3300 MHz to 6000 MHz	
	continuous wave (CW)	-112 dBm to -7 dBm
	peak envelope power (PEP)	up to -7 dBm
	overranging (PEP)	up to +3 dBm
	maximum input DC level	0 V DC

Output level uncertainty	in temperature range +20 °C to +35 °C, no overranging	
RF1 COM, RF2 COM	output level > -120 dBm	
	70 MHz to 100 MHz	< 1.2 dB ¹
	100 MHz to 3300 MHz	< 0.6 dB ¹
	3300 MHz to 6000 MHz	< 1.2 dB ¹
RF1 OUT	output level > -112 dBm	
	70 MHz to 100 MHz	< 1.6 dB ¹
	100 MHz to 3300 MHz	< 0.8 dB ¹
	3300 MHz to 6000 MHz	< 1.6 dB ¹

Output level uncertainty	in temperature range +5 °C to +45 °C, no overranging	
RF1 COM, RF2 COM	output level > -120 dBm	
	70 MHz to 100 MHz	< 2.0 dB ¹
	100 MHz to 3300 MHz	< 1.0 dB ¹
	3300 MHz to 6000 MHz	< 2.0 dB ¹
RF1 OUT	output level > -112 dBm	
	70 MHz to 100 MHz	< 2.0 dB ¹
	100 MHz to 3300 MHz	< 1.0 dB ¹
	3300 MHz to 6000 MHz	< 2.0 dB ¹

¹ Valid for a 12-month calibration interval.

Output level linearity with fixed RF output attenuator setting	in temperature range +20 °C to +35 °C, GPRF generator list mode, level range 0 dB to –30 dB	
RF1 COM, RF2 COM	no overranging	< 0.2 dB, typ. < 0.1 dB
Output level resolution		0.01 dB
Output level repeatability	typical values after 1 h warm-up time, always returning to same level and frequency, no temperature change, insignificant time change	
	output level \geq –80 dBm	< 0.01 dB
	output level < –80 dBm	< 0.05 dB
VSWR		
RF1 COM, RF2 COM	70 MHz to 3300 MHz	< 1.2
	3300 MHz to 5000 MHz	< 1.5
	5000 MHz to 6000 MHz	< 1.6
RF1 OUT	70 MHz to 3300 MHz	< 1.5
	3300 MHz to 5000 MHz	< 1.5
	5000 MHz to 6000 MHz	< 1.6
Attenuation of 2nd harmonic		
RF1 COM, RF2 COM	70 MHz to 6000 MHz, P < –10 dBm	> 30 dB
RF1 OUT	70 MHz to 6000 MHz, P < 0 dBm	> 30 dB
Attenuation of 3rd harmonic		
RF1 COM, RF2 COM	70 MHz to 6000 MHz, P < –10 dBm	> 40 dB
RF1 OUT	70 MHz to 6000 MHz, P < 0 dBm	> 40 dB
Attenuation of nonharmonics	> 5 kHz offset from carrier, for output level > –40 dBm, for full scale CW signal	
	400 MHz to 3300 MHz, except $f_{\text{nonharmonic}} = 3900 \text{ MHz} - f_{\text{carrier}}$, except $f_{\text{nonharmonic}} = 3900 \text{ MHz}$, except $f_{\text{carrier}} = (899 \text{ to } 901) \text{ MHz} + n \times 800 \text{ MHz}$ with $n = 1, 2, 3$	> 60 dB
	3300 MHz to 3600 MHz	> 25 dB
	3600 MHz to 6000 MHz, except $f_{\text{nonharmonic}} = 2 \times f_{\text{carrier}} - 6400 \text{ MHz}$	> 40 dB
Phase noise	single sideband, 70 MHz to 3300 MHz	
Carrier offset	$\geq 1 \text{ MHz}$	< –120 dBc, 1 Hz
Phase noise	single sideband, 3300 MHz to 6000 MHz	
Carrier offset	$\geq 1 \text{ MHz}$	< –117 dBc, 1 Hz
Signal-to-noise ratio	70 MHz to 3300 MHz	
RF1 COM, RF2 COM	5 MHz offset from carrier, for output level > –30 dBm	> 95 dB, typ. > 101 dB, 1 kHz (> 125 dB, typ. > 131 dB, 1 Hz)
Signal-to-noise ratio	3300 MHz to 6000 MHz	
RF1 COM, RF2 COM	5 MHz offset from carrier, for output level > –30 dBm	> 92 dB, 1 kHz

**Modulation source: arbitrary waveform generator (ARB)
(R&S® CMW-B110A/R&S® CMW-B110D option)**

Memory size	R&S®CMW-B110A	1.024 Gbyte
	R&S®CMW-B110D	4.096 Gbyte
Word length	I	16 bit
	Q	16 bit
	marker	4 bit to 16 bit
Sample length	with 4-bit marker	up to 227.55 Msample
Sample rate	minimum	400 Hz
	maximum	100 MHz
Maximum possible RF bandwidth	depending on arbitrary waveform file	80 MHz
Trigger		
Trigger sources		BASE: external TRIG A, BASE: external TRIG B

RF analyzer

VSWR		
RF1 COM, RF2 COM	70 MHz to 3300 MHz	< 1.2
	3300 MHz to 5000 MHz	< 1.5
	5000 MHz to 6000 MHz	< 1.6
Inherent spurious response	without input signal, 70 MHz to 6000 MHz, except 4000 MHz, 4800 MHz, 5162.5 MHz, 5600 MHz, 6000 MHz	
	expected nominal power setting ≤ -10 dBm	< -100 dBm
	expected nominal power setting > -10 dBm	< -90 dB below expected nominal power setting
Spurious response	for full scale single tone input signal 70 MHz to 3300 MHz, except $f_{in} = 1962.5$ MHz and 3925 MHz, except $f_{in} = 1962.5$ MHz + $f_{selected}$	< -55 dB
	3300 MHz to 3700 MHz, except $f_{in} = 6400$ MHz - $f_{selected}$, except $f_{in} = 6400$ MHz - $0.5 \times f_{selected}$	< -40 dB
	3700 MHz to 6000 MHz, except $f_{in} = 6400$ MHz - $0.5 \times f_{selected}$	< -40 dB
Harmonic response RF1 COM, RF2 COM	2nd harmonic	
	$f_{in} = 70$ MHz to 1650 MHz, $f_{selected} = 140$ MHz to 3300 MHz	< -30 dB
	$f_{in} = 1650$ MHz to 3000 MHz, $f_{selected} = 3300$ MHz to 6000 MHz	< -30 dB
Harmonic response RF1 COM, RF2 COM	3rd harmonic	
	$f_{in} = 70$ MHz to 900 MHz, $f_{selected} = 210$ MHz to 2700 MHz	< -50 dB
	$f_{in} = 900$ MHz to 1100 MHz, $f_{selected} = 2700$ MHz to 3300 MHz	< -45 dB
	$f_{in} = 1100$ MHz to 2000 MHz, $f_{selected} = 3300$ MHz to 6000 MHz	< -50 dB
Phase noise Carrier offset	single sideband, 70 MHz to 3300 MHz	
	≥ 1 MHz	< -120 dBc, 1 Hz
Phase noise Carrier offset	single sideband, 3300 MHz to 6000 MHz	
	≥ 1 MHz	< -117 dBc, 1 Hz

Trigger		
Trigger sources		BASE: external TRIG A, BASE: external TRIG B, GPRF: free run, GPRF: IF power, BB generators, BB signaling

Power meter

Frequency range		70 MHz to 3300 MHz, up to 6000 MHz with the R&S®CMW-KB036 option
Frequency resolution		0.1 Hz
Resolution bandwidths		Gaussian, 1 kHz to 10 MHz, in 1/3/5 steps, bandpass, 1 kHz to 30 MHz, in 1/3/5 steps, RRC, $\alpha = 0.1$, 3.84 MHz, RRC, $\alpha = 0.22$, WCDMA filter, 1.2288 MHz, CDMA filter
Expected nominal power setting range	for ADC full scale	
RF1 COM, RF2 COM	70 MHz to 100 MHz	-37 dBm to +42 dBm ²
	100 MHz to 3300 MHz	-47 dBm to +42 dBm ²
	3300 MHz to 6000 MHz	-37 dBm to +42 dBm ²

Level range		
RF1 COM, RF2 COM	70 MHz to 100 MHz	
	continuous power (CW)	-74 dBm ³ to +34 dBm
	peak envelope power (PEP)	up to +42 dBm ²
	100 MHz to 3300 MHz	
	continuous power (CW)	-84 dBm ³ to +34 dBm
	peak envelope power (PEP)	up to +42 dBm ²
	3300 MHz to 6000 MHz	
	continuous power (CW)	-74 dBm ³ to +34 dBm
	peak envelope power (PEP)	up to +42 dBm ²
	maximum input DC level	0 V DC

Level uncertainty	in temperature range +20 °C to +35 °C	
RF1 COM, RF2 COM	70 MHz to 100 MHz	< 1.0 dB ⁴
	100 MHz to 3300 MHz	< 0.5 dB ⁴
	3300 MHz to 6000 MHz	< 1.0 dB ⁴

Level uncertainty	in temperature range +5 °C to +45 °C	
RF1 COM, RF2 COM	70 MHz to 100 MHz	< 1.2 dB ⁴
	100 MHz to 3300 MHz	< 0.7 dB ⁴
	3300 MHz to 6000 MHz	< 1.2 dB ⁴

Level linearity with fixed expected nominal power setting	in temperature range +20 °C to +35 °C	
RF1 COM, RF2 COM	level range 0 dB to -40 dB	< 0.15 dB, typ. < 0.1 dB

Level resolution		0.01 dB
-------------------------	--	---------

Level repeatability	typical values after 1 h warm-up time, always returning to same level and frequency, no temperature change, insignificant time change	
	input level ≥ -40 dBm	< 0.01 dB
	input level < -40 dBm	< 0.03 dB

² The maximum permissible continuous power is +34 dBm due to thermal limits.

³ $RBW \rightarrow 1$ kHz.

⁴ Valid for a 12-month calibration interval.

Dynamic range	70 MHz to 3300 MHz, <i>RBW</i> → 1 kHz, with fixed expected nominal power setting	> 100 dB
Expected nominal power setting for full dynamic range		
RF1 COM, RF2 COM		-8 dBm to +42 dBm ⁵

Dynamic range	3300 MHz to 6000 MHz, <i>RBW</i> → 1 kHz, with fixed expected nominal power setting	> 97 dB
Expected nominal power setting for full dynamic range		
RF1 COM, RF2 COM		+2 dBm to +42 dBm ⁵

Spectrum measurements

FFT spectrum analyzer		
Frequency range		70 MHz to 3300 MHz, up to 6000 MHz with the R&S®CMW-KB036 option
Frequency span		1.25 MHz, 2.5 MHz, 5 MHz, 10 MHz, 20 MHz, 40 MHz
FFT length		1k, 2k, 4k, 8k, 16k
Detector		peak, RMS

Dynamic range	70 MHz to 3300 MHz, <i>for FFT length</i> → 16k and <i>span</i> → 5 MHz (equivalent to <i>RBW</i> → 781 Hz)	> 100 dB
Expected nominal power setting for full dynamic range		
RF1 COM, RF2 COM		-8 dBm to +42 dBm ⁵

Dynamic range	3300 MHz to 6000 MHz, <i>for FFT length</i> → 16k and <i>span</i> → 5 MHz (equivalent to <i>RBW</i> → 781 Hz)	> 97 dB
Expected nominal power setting for full dynamic range		
RF1 COM, RF2 COM		+2 dBm to +42 dBm ⁵

RF spectrum analyzer (R&S®CMW-KM010 option)		
Frequency range		70 MHz to 3300 MHz, up to 6000 MHz with the R&S®CMW-KB036 option
Frequency span		0 Hz (zero span), 500 Hz to 3230 MHz, up to 5930 MHz with the R&S®CMW-KB036 option
Resolution bandwidth (RBW)		100 Hz to 10 MHz (additional 40 MHz in zero span)
Video bandwidth (VBW)		10 Hz to 10 MHz
Sweep time	frequency sweep, depending on RBW, VBW and span	500 µs to 2000 s
	zero span, depending on RBW and VBW	80 µs to 2000 s
Detector		average, RMS, sample, min. peak, max. peak, auto peak
Trigger	frequency sweep	free run
	zero span	video, BASE: external TRIG A, B all R&S®CMW internal trigger sources

Dynamic range	70 MHz to 3300 MHz, <i>RBW</i> → 1 kHz, <i>detector</i> → RMS	> 100 dB
Expected nominal power setting for full dynamic range		
RF1 COM, RF2 COM		-8 dBm to +42 dBm ⁵

Dynamic range	3300 MHz to 6000 MHz, <i>RBW</i> → 1 kHz, <i>detector</i> → RMS	> 97 dB
Expected nominal power setting for full dynamic range		
RF1 COM, RF2 COM		+2 dBm to +42 dBm ⁵

⁵ The maximum permissible continuous power is +34 dBm due to thermal limits.

Level range		see general technical specifications
Level uncertainty	for center frequency and <i>detector</i> → <i>peak</i>	see general technical specifications
Inherent spurious response		see general technical specifications
Spurious response		see general technical specifications
Harmonic response		see general technical specifications
Phase noise		see general technical specifications

Possible configurations with two RF paths ⁶

Necessary hardware (H570, H590X):

Selections: R&S[®]CMW-S590A RF frontend (BASIC) or R&S[®]CMW-S590D RF frontend (ADV.) and R&S[®]CMW-S570 RF TRX.

Options: R&S[®]CMW-B590A RF frontend (BASIC) or R&S[®]CMW-B590D RF frontend (ADV.) and R&S[®]CMW-B570 RF TRX.

Configuration with two H570 (RF TRX) and two H590A (RF frontend (BASIC))

The R&S[®]CMW-B570 and R&S[®]CMW-B590A options make the second RF path (RF path 2) available on the front of the instrument with three additional RF connectors, i.e. RF3 COM, RF4 COM and RF3 OUT.

RF3 COM	equivalent to RF1 COM	see general technical specifications
RF4 COM	equivalent to RF2 COM	see general technical specifications
RF3 OUT	equivalent to RF1 OUT	see general technical specifications

Configuration with two H570 (RF TRX) and one H590D (RF frontend (ADV.))

The R&S[®]CMW-B570 option and R&S[®]CMW-S590D selection make the second RF path (RF path 2) available on the front of the instrument at connectors RF1 COM, RF2 COM and RF1 OUT.

RF path 1 and RF path 2 routed to separate connectors

RF generator 1 and RF generator 2	switchable to RF1 COM, RF2 COM, RF1 OUT	see general technical specifications
RF analyzer 1 and RF analyzer 2	switchable to RF1 COM, RF2 COM	see general technical specifications
Expected nominal power setting range		see general technical specifications, + 3 dB for lower level limit value
Expected nominal power setting for full dynamic range		see general technical specifications, + 3 dB for lower level limit value
Level range		see general technical specifications, + 3 dB (typ. + 2 dB) for lower level limit value

RF path 1 and RF path 2 routed to common connector

RF generator 1 and RF generator 2	switchable to RF1 COM, RF2 COM, RF1 OUT	see general technical specifications
Output level range	peak envelope power (PEP)	the specified value is valid for the total power of the two RF generators, see general technical specifications
Output level uncertainty	for each carrier	see general technical specifications, + 0.2 dB
Signal-to-noise ratio	for the carrier with the highest output level (at least 3 dB higher than the other carrier)	see general technical specifications
RF analyzer 1 and RF analyzer 2	switchable to RF1 COM, RF2 COM	see general technical specifications
Level uncertainty	70 MHz to 3300 MHz	see general technical specifications, + 0.2 dB
	3300 MHz to 6000 MHz	see general technical specifications, + 0.3 dB
Expected nominal power setting range		see general technical specifications, + 3 dB for lower level limit value
Expected nominal power setting for full dynamic range		see general technical specifications, + 3 dB for lower level limit value
Level range		see general technical specifications, + 3 dB (typ. + 2 dB) for lower level limit value

⁶ R&S[®]CMW500 and R&S[®]CMW270 only.

Possible configurations with four RF paths ⁷

Necessary hardware (H570, H571B, H590D):

Selections: R&S®CMW-S590D RF frontend (ADV.) and R&S®CMW-S570 RF TRX.

Options: R&S®CMW-B590D RF frontend (ADV.) and:

- one R&S®CMW-B570 RF TRX and two R&S®CMW-B571B RF TX
- or three R&S®CMW-B570 RF TRX.

Configuration with two H570 (RF TRX), two H571B (RF TX) and two H590D (RF frontend (ADV.))

The R&S®CMW-B570 option, two R&S®CMW-B571 options and R&S®CMW-B590D option make the four RF paths (RF path 1 RX and TX, RF path 2 RX and TX, RF path 3 TX only, RF path 4 TX only) available on the front of the instrument at connectors RF1 COM, RF2 COM, RF1 OUT and RF3 COM, RF4 COM, RF3 OUT.

RF path 1, 2, 3 and 4 routed to separate connectors

RF generator 1 and RF generator 3	switchable to RF1 COM, RF2 COM, RF1 OUT	see general technical specifications
RF generator 2 and RF generator 4	switchable to RF3 COM, RF4 COM, RF3 OUT	see general technical specifications
RF analyzer 1	switchable to RF1 COM, RF2 COM	see general technical specifications
Expected nominal power setting range		see general technical specifications, + 3 dB for lower level limit value
Expected nominal power setting for full dynamic range		see general technical specifications, + 3 dB for lower level limit value
Level range		see general technical specifications, + 3 dB (typ. + 2 dB) for lower level limit value
RF analyzer 2	switchable to RF3 COM, RF4 COM	see general technical specifications
Expected nominal power setting range		see general technical specifications, + 3 dB for lower level limit value
Expected nominal power setting for full dynamic range		see general technical specifications, + 3 dB for lower level limit value
Level range		see general technical specifications, + 3 dB (typ. + 2 dB) for lower level limit value

RF path 1, RF path 3 routed to common connector and RF path 2, RF path 4 routed to common connector

RF generator 1 and RF generator 3	switchable to RF1 COM, RF2 COM, RF1 OUT	see general technical specifications
Output level range	peak envelope power (PEP)	the specified value is valid for the total power of the two RF generators, see general technical specifications
Output level uncertainty	for each carrier	see general technical specifications, + 0.2 dB
Signal-to-noise ratio	for the carrier with the highest output level (at least 3 dB higher than the other carrier)	see general technical specifications
RF generator 2 and RF generator 4	switchable to RF3 COM, RF4 COM, RF3 OUT	see general technical specifications
Output level range	peak envelope power (PEP)	the specified value is valid for the total power of the two RF generators, see general technical specifications
Output level uncertainty	for each carrier	see general technical specifications, + 0.2 dB
Signal-to-noise ratio	for the carrier with the highest output level (at least 3 dB higher than the other carrier)	see general technical specifications

⁷ R&S®CMW500 only.

RF analyzer 1	switchable to RF1 COM, RF2 COM	see general technical specifications
Level uncertainty	70 MHz to 3300 MHz	see general technical specifications, + 0.2 dB
	3300 MHz to 6000 MHz	see general technical specifications, + 0.3 dB
Expected nominal power setting range		see general technical specifications, + 3 dB for lower level limit value
Expected nominal power setting for full dynamic range		see general technical specifications, + 3 dB for lower level limit value
Level range		see general technical specifications, + 3 dB (typ. + 2 dB) for lower level limit value

Configuration with four H570 (RF TRX) and two H590D (RF frontend (ADV.))

The three R&S®CMW-B570 options and R&S®CMW-B590D option make the four RF paths (RF path 1 RX and TX, RF path 2 RX and TX, RF path 3 RX and TX, RF path 4 RX and TX) available on the front of the instrument at connectors RF1 COM, RF2 COM, RF1 OUT and RF3 COM, RF4 COM, RF3 OUT.

RF path 1, 2, 3 and 4 routed to separate connectors

RF generator 1 and RF generator 3	switchable to RF1 COM, RF2 COM, RF1 OUT	see general technical specifications
RF generator 2 and RF generator 4	switchable to RF3 COM, RF4 COM, RF3 OUT	see general technical specifications
RF analyzer 1 and RF analyzer 3	switchable to RF1 COM, RF2 COM	see general technical specifications
Expected nominal power setting range		see general technical specifications, + 3 dB for lower level limit value
Expected nominal power setting for full dynamic range		see general technical specifications, + 3 dB for lower level limit value
Level range		see general technical specifications, + 3 dB (typ. + 2 dB) for lower level limit value
RF analyzer 2 and RF analyzer 4	switchable to RF3 COM, RF4 COM	see general technical specifications
Expected nominal power setting range		see general technical specifications, + 3 dB for lower level limit value
Expected nominal power setting for full dynamic range		see general technical specifications, + 3 dB for lower level limit value
Level range		see general technical specifications, + 3 dB (typ. + 2 dB) for lower level limit value

RF path 1, RF path 3 routed to common connector and RF path 2, RF path 4 routed to common connector

RF generator 1 and RF generator 3	switchable to RF1 COM, RF2 COM, RF1 OUT	see general technical specifications
Output level range	peak envelope power (PEP)	the specified value is valid for the total power of the two RF generators, see general technical specifications
Output level uncertainty	for each carrier	see general technical specifications, + 0.2 dB
Signal-to-noise ratio	for the carrier with the highest output level (at least 3 dB higher than the other carrier)	see general technical specifications
RF generator 2 and RF generator 4	switchable to RF3 COM, RF4 COM, RF3 OUT	see general technical specifications
Output level range	peak envelope power (PEP)	the specified value is valid for the total power of the two RF generators, see general technical specifications
Output level uncertainty	for each carrier	see general technical specifications, + 0.2 dB
Signal-to-noise ratio	for the carrier with the highest output level (at least 3 dB higher than the other carrier)	see general technical specifications

RF analyzer 1 and RF analyzer 3	switchable to RF1 COM, RF2 COM	see general technical specifications
Level uncertainty	70 MHz to 3300 MHz	see general technical specifications, + 0.2 dB
	3300 MHz to 6000 MHz	see general technical specifications, + 0.3 dB
Expected nominal power setting range		see general technical specifications, + 3 dB for lower level limit value
Expected nominal power setting for full dynamic range		see general technical specifications, + 3 dB for lower level limit value
Level range		see general technical specifications, + 3 dB (typ. + 2 dB) for lower level limit value
RF analyzer 2 and RF analyzer 4	switchable to RF3 COM, RF4 COM	see general technical specifications
Level uncertainty	70 MHz to 3300 MHz	see general technical specifications, + 0.2 dB
	3300 MHz to 6000 MHz	see general technical specifications, + 0.3 dB
Expected nominal power setting range		see general technical specifications, + 3 dB for lower level limit value
Expected nominal power setting for full dynamic range		see general technical specifications, + 3 dB for lower level limit value
Level range		see general technical specifications, + 3 dB (typ. + 2 dB) for lower level limit value

Timebase

Timebase TCXO

Max. frequency drift	in temperature range +5 °C to +45 °C	$\pm 1 \times 10^{-6}$
Max. aging	at +25 °C, after 14 days of continuous operation	$\pm 1 \times 10^{-6}$ /year

Timebase basic OCXO (R&S® CMW-B690A option)

Max. frequency drift	in temperature range +5 °C to +45 °C	$\pm 5 \times 10^{-8}$
Retrace	at +25 °C, after 24 hours power on / 2 hours power off / 1 hour power on	$\pm 2 \times 10^{-8}$
Max. aging	at +25 °C, after 10 days of continuous operation	$\pm 1 \times 10^{-7}$ /year, $\pm 1 \times 10^{-9}$ /day
Warm-up time	at +25 °C, the frequency is in the range that is 10 times the frequency drift ($\pm 5 \times 10^{-7}$)	approx. 10 min

Timebase highly stable OCXO (R&S® CMW-B690B option)

Max. frequency drift	in temperature range +5 °C to +45 °C, referenced to +25 °C with instrument orientation	$\pm 5 \times 10^{-9}$ $\pm 1 \times 10^{-9}$
Retrace	at +25 °C, after 24 hours power on / 2 hours power off / 1 hour power on	$\pm 5 \times 10^{-9}$
Max. aging	at +25 °C, after 10 days of continuous operation	$\pm 3 \times 10^{-8}$ /year, $\pm 5 \times 10^{-10}$ /day
Warm-up time	at +25 °C, the frequency is in the range that is 10 times the frequency drift ($\pm 5 \times 10^{-8}$)	approx. 10 min

Reference frequency inputs/outputs

Synchronization input		BNC connector REF IN, rear panel
Frequency	sine wave square wave (TTL level)	10 MHz to 80 MHz, step: 1 Hz 1 MHz to 80 MHz, step: 1 Hz
Max. frequency variation		$\pm 10 \times 10^{-6}$
Input voltage range		0.5 V to 2 V, RMS
Impedance		50 Ω

Synchronization output 1		BNC connector REF OUT 1, rear panel
Frequency		10 MHz from internal reference or frequency at synchronization input
Output voltage		> 1.4 V, peak-to-peak
Impedance		50 Ω

Audio specifications (prerequisite: R&S® CMW-B400B)

Audio analyzer

Statistics

Statistical count		1 to 1000
Values		current, average, extremum, standard deviation

Audio filter, weighting

Lowpass		off, 3 kHz, 4 kHz, 15 kHz
Highpass		off, 6 Hz, 50 Hz, 300 Hz
Weighting filter		off, A-weighting, CCITT, C-message

Connectors AF 1 IN / AF 2 IN

Input impedance		100 k Ω 15 pF
-----------------	--	------------------------

AF voltmeter

Frequency range		50 Hz to 21 kHz
Level range		50 μ V to 30 V
Level resolution	at level < 1 mV	1 μ V
	at level \geq 1 mV	0.1 %
Level uncertainty	at 1 mV \leq level < 20 mV	< 1.3% + resolution
	at 20 mV \leq level \leq 20 V	< 1.0 % + resolution

THD+N and THD meter

Measurement bandwidth		21 kHz
Frequency range		100 Hz to 10.5 kHz
Level range		10 mV to 30 V
Resolution		0.01 %
Inherent distortion THD+N	at 100 mV \leq level \leq 20 V	< 0.05 %
Inherent distortion THD	at 100 mV \leq level \leq 20 V	< 0.025 %
Uncertainty	at 100 mV \leq level \leq 2 V	< 1 % + inherent distortion
	at 2 V \leq level \leq 20 V	< 2 % + inherent distortion

Audio generator

Connectors AF 1 OUT / AF 2 OUT

Output impedance		< 4 Ω
Maximum output current		20 mA

AF sine generator

Frequency range		20 Hz to 21 kHz
Frequency uncertainty		same as timebase, see base unit specifications
Frequency resolution		1 Hz
Level range		10 μ V to 5 V
Level resolution	at level < 10 mV	10 μ V
	at level \geq 10 mV	0.1 %
Level uncertainty	at level \geq 1 mV and frequency \leq 10 kHz	\leq 1.5 % + resolution
THD+N	at level \geq 100 mV, into load \geq 600 Ω , measurement bandwidth: 21.9 kHz	\leq 0.05 %
THD	at level \geq 100 mV, into load \geq 600 Ω , measurement bandwidth: 21.9 kHz	\leq 0.025 %

Digital interface unbalanced

BNC rear panel connectors

Connector SPDIF IN		
Input impedance		75 Ω

Connector SPDIF OUT		
Output impedance		75 Ω

Max. sample rate		48 kHz
Max. resolution		24 bits PCM
Output level		0.5 V, peak-to-peak
Max. output		0.6 V, peak-to-peak
Max. current		8 mA
Min input		0.2 V, peak-to-peak
Modulation		biphase mark code
Usage		audio analysis, digital audio tape (DAT)

GSM specifications – mobile station test ⁸

GSM RF generator (prerequisite: R&S®CMW-B110A/R&S®CMW-B110D option)

Frequency range	GSM450 band	460 MHz to 468 MHz
	GSM480 band	488 MHz to 496 MHz
	GSM750 band	747 MHz to 762 MHz
	GSM850 band	869 MHz to 894 MHz
	GSM900 band	921 MHz to 960 MHz
	GSM1800 band	1805 MHz to 1880 MHz
	GSM1900 band	1930 MHz to 1990 MHz

GSM GEN (R&S®CMW-KG200 option)

Output level range	depending on PAR	see general technical specifications
Output level uncertainty		see general technical specifications
Output level resolution		see general technical specifications

Signal quality		
Phase error	GMSK	< 1°, RMS < 4°, peak
Error vector magnitude (EVM)	8PSK	< 2 %, RMS

GSM WinIQSIM2™ (R&S®CMW-KW200 option), GSM EDGE EVO WinIQSIM2™ (R&S®CMW-KW201 option)

Arbitrary waveform files	GMSK, $B \times T = 0.3$, with the R&S®CMW-KW200 option	GSM_GMSK.WV (PAR = 0 dB), GMSKDIGMOD.WV (PAR = 0 dB)
	8PSK, with the R&S®CMW-KW200 option	GSM_EDGE.WV (PAR = 3.23 dB), EDGEDIGMOD.WV (PAR = 3.22 dB)
Arbitrary waveform files	16QAM, with the R&S®CMW-KW200 and R&S®CMW-KW201 options	EDGE_EVO_16QAM_A.WV (PAR = 4.70 dB)
	32QAM, with the R&S®CMW-KW200 and R&S®CMW-KW201 options	EDGE_EVO_32QAM_B.WV (PAR = 5.37 dB)

Output level range	depending on PAR	see general technical specifications
Output level uncertainty	with the R&S®CMW-KW200 option, waveform files used: GMSKDIGMOD.WV or EDGEDIGMOD.WV	see general technical specifications
	with the R&S®CMW-KW200 and R&S®CMW-KW201 options, waveform files used: EDGE_EVO_16QAM_A.WV, EDGE_EVO_32QAM_B.WV	see general technical specifications
Output level resolution		see general technical specifications

⁸ R&S®CMW500 and R&S®CMW280 only.

Signal quality		
Phase error	GMSK with the R&S®CMW-KW200 option, waveform file used: GSM_GMSK.WV	< 1°, RMS < 4°, peak
Error vector magnitude (EVM)	8PSK with the R&S®CMW-KW200 option, waveform file used: GSM_EDGE.WV	< 2 %, RMS
	16QAM / 32QAM level A with the R&S®CMW-KW200 and R&S®CMW-KW201 options, waveform file used: EDGE_EVO_16QAM_A.WV	< 2 %, RMS
	QPSK / 16QAM / 32QAM level B with the R&S®CMW-KW200 and R&S®CMW-KW201 options, waveform file used: EDGE_EVO_32QAM_B.WV	< 2 %, RMS

GSM RF analyzer (R&S®CMW-KM200 option) and GSM EDGE EVO A analyzer (R&S®CMW-KM201 option)

Frequency range	GSM450 band	450 MHz to 458 MHz
	GSM480 band	478 MHz to 486 MHz
	GSM750 band	777 MHz to 792 MHz
	GSM850 band	824 MHz to 849 MHz
	GSM900 band	876 MHz to 915 MHz
	GSM1800 band	1710 MHz to 1785 MHz
	GSM1900 band	1850 MHz to 1910 MHz

Trigger		
Trigger sources		BASE: external TRIG A, BASE: external TRIG B, GPRF: BB generator, GSM: free run, GSM: IF power, GSM: acquisition

Modulation analysis

Level range		-28 dBm to +42 dBm ⁹
Analysis mode	with the R&S®CMW-KW200 option	GMSK, 8PSK
	with the R&S®CMW-KW200 and R&S®CMW-KW201 options	GMSK, 8PSK, 16QAM (level A)
Inherent phase error	GMSK	< 0.6°, RMS
		< 2°, peak
Inherent error vector magnitude (inherent EVM)	8PSK, 16QAM (level A)	< 0.8 %, RMS
Frequency measurement uncertainty		< 20 Hz + drift of timebase, see general technical specifications
Inherent I/Q offset		< -50 dB
Filter	GMSK	bandpass, 900 kHz, RRC filter, $\alpha = 0.16$
	8PSK, 16QAM (level A)	windowed raised-cosine filter in line with 3GPP TS 45.005

Burst power measurement		
Level uncertainty	bandpass, 900 kHz, RRC filter, $\alpha = 0.16$	see general technical specifications

⁹ The maximum permissible continuous power is +34 dBm due to thermal limits.

Power versus time measurement

Filter	selectable	Gaussian, 500 kHz or 1 MHz
Dynamic range	<i>filter</i> → 500 kHz, Gaussian, with fixed expected nominal power setting	
	GMSK	> 72 dB, RMS
	8PSK, 16QAM (level A)	> 69 dB, RMS
Expected nominal power setting for full dynamic range	RF1 COM, RF2 COM	-8 dBm to +42 dBm ¹⁰
Relative measurement uncertainty	result > -40 dB	typ. < 0.1 dB
	-60 dB ≤ result ≤ -40 dB	typ. < 0.5 dB

Burst power measurement		
Level range		-50 dBm to +42 dBm ¹⁰
Level uncertainty	<i>filter</i> → 500 kHz or 1 MHz, Gaussian	see general technical specifications

Spectrum due to modulation measurement

Expected nominal power setting for full dynamic range	RF1 COM, RF2 COM	-8 dBm to +42 dBm ¹⁰
Test method		relative measurement, averaging
Filter		Gaussian, 30 kHz, 5 pole
Measurement	at an offset of ±	100/200/250/400/600/800/1000/1200/ 1400/1600/1800 kHz
Dynamic range	offset ≥ 1200 kHz	
	GMSK	> 74 dB
	8PSK, 16QAM (level A)	> 70 dB

Spectrum due to switching measurement

Expected nominal power setting for full dynamic range	RF1 COM, RF2 COM	-8 dBm to +42 dBm ¹⁰
Test method		absolute measurement, max. hold
Filter		Gaussian, 30 kHz, 5 pole
Measurement	at an offset of ±	400/600/1200/1800 kHz
Dynamic range	offset ≥ 1200 kHz	
	GMSK	> 72 dB
	8PSK, 16QAM (level A)	> 68 dB

GSM signaling (prerequisite: R&S[®]CMW-KS200, R&S[®]CMW-KS201, R&S[®]CMW-KS203, R&S[®]CMW-B200A, R&S[®]CMW-B210A options; additionally R&S[®]CMW-KS210 option and R&S[®]CMW-KS211)

Frequency range		
GSM850 band, GSM900 band, GSM1800 band, GSM1900 band	DL UL	see GSM RF generator specifications see GSM RF analyzer specifications
Frequency setting		channel number
Output level range	depending on PAR and additional 6 dB level margin	see general technical specifications
	with DLDC: depending on PAR and additional 9.3 dB level margin	see general technical specifications
Output level resolution		see general technical specifications
Output level uncertainty		see general technical specifications
Modulation		
Inherent phase error	GMSK	< 1°, RMS < 4°, peak

¹⁰ The maximum permissible continuous power is +34 dBm due to thermal limits.

WCDMA specifications – mobile station (UE) test ¹¹

Standard		3GPP FDD
----------	--	----------

WCDMA RF generator

(prerequisite: R&S[®]CMW-B110A/R&S[®]CMW-B110D option)

Frequency range	WCDMA band 1	2112.4 MHz to 2167.6 MHz
	WCDMA band 2	1932.4 MHz to 1987.6 MHz
	WCDMA band 3	1807.4 MHz to 1877.6 MHz
	WCDMA band 4	2112.4 MHz to 2152.6 MHz
	WCDMA band 5	871.4 MHz to 891.6 MHz
	WCDMA band 6	877.4 MHz to 882.6 MHz
	WCDMA band 7	2622.4 MHz to 2687.6 MHz
	WCDMA band 8	927.4 MHz to 957.6 MHz
	WCDMA band 9	1847.4 MHz to 1877.4 MHz
	WCDMA band 10	2112.4 MHz to 2167.6 MHz
	WCDMA band 11	1478.4 MHz to 1498.4 MHz
	WCDMA band 12	730.4 MHz to 743.6 MHz
	WCDMA band 13	748.4 MHz to 753.6 MHz
	WCDMA band 14	760.4 MHz to 765.6 MHz
	WCDMA band S	2182.4 MHz to 2197.6 MHz
	WCDMA band S170	2180 MHz to 2190 MHz
WCDMA band S190	2190 MHz to 2200 MHz	

WCDMA GEN (R&S[®]CMW-KG400 option), WCDMA HSPA GEN (R&S[®]CMW-KG401 option)

Output level range	depending on PAR	see general technical specifications
Output level uncertainty		see general technical specifications
Output level resolution		see general technical specifications

Signal quality		
Error vector magnitude (EVM)	composite EVM	< 2 %, RMS

WCDMA WiniQSIM2™ (R&S[®]CMW-KW400 option), WCDMA HSDPA WiniQSIM2™ (R&S[®]CMW-KW401 option), WCDMA HSUPA WiniQSIM2™ (R&S[®]CMW-KW402 option), WCDMA HSPA+ WiniQSIM2™ (R&S[®]CMW-KW403 option)

Arbitrary waveform files	with the R&S [®] CMW-KW400 option	TM4CPICH.WV (PAR = 8.34 dB), 3GPPDEFAULT.WV (PAR = 10.65 dB)
	with the R&S [®] CMW-KW400 and R&S [®] CMW-KW401 options	WCDMA_DL_HSDPA.WV (PAR = 10.08 dB)
	with the R&S [®] CMW-KW400 and R&S [®] CMW-KW401 and R&S [®] CMW-KW402 options	WCDMA_DL_HSUPA.WV (PAR = 10.12 dB)

Output level range	depending on PAR	see general technical specifications
Output level uncertainty	with the R&S [®] CMW-KW400 option, waveform file used: 3GPPDEFAULT.WV	see general technical specifications
	with the R&S [®] CMW-KW401 option, waveform file used: WCDMA_DL_HSDPA.WV	see general technical specifications
	with the R&S [®] CMW-KW402 option, waveform file used: WCDMA_DL_HSUPA.WV	see general technical specifications
	with the R&S [®] CMW-KW400 and R&S [®] CMW-KW401 and R&S [®] CMW-KW402 and R&S [®] CMW-KW403 options	see general technical specifications
Output level resolution		see general technical specifications

¹¹ R&S[®]CMW500 and R&S[®]CMW280 only.

Signal quality		
Error vector magnitude (EVM)	composite EVM, with the R&S®CMW-KW400 option, waveform file used: TM4CPICH.WV	< 2 %, RMS
	composite EVM, with the R&S®CMW-KW401 option, waveform file used: WCDMA_DL_HSDPA.WV	< 2 %, RMS
	composite EVM, with the R&S®CMW-KW402 option, waveform file used: WCDMA_DL_HSUPA.WV	< 2 %, RMS
	with the R&S®CMW-KW400 and R&S®CMW-KW401 and R&S®CMW-KW402 and R&S®CMW-KW403 options	< 2 %, RMS

WCDMA RF analyzer (R&S®CMW-KM400, R&S®CMW-KM401, R&S®CMW-KM403 options)

Frequency range	WCDMA band 1	1922.4 MHz to 1977.6 MHz
	WCDMA band 2	1852.4 MHz to 1907.6 MHz
	WCDMA band 3	1712.4 MHz to 1782.6 MHz
	WCDMA band 4	1712.4 MHz to 1752.6 MHz
	WCDMA band 5	826.4 MHz to 846.6 MHz
	WCDMA band 6	832.4 MHz to 837.6 MHz
	WCDMA band 7	2502.4 MHz to 2567.6 MHz
	WCDMA band 8	882.4 MHz to 912.6 MHz
	WCDMA band 9	1752.4 MHz to 1782.4 MHz
	WCDMA band 10	1712.4 MHz to 1767.6 MHz
	WCDMA band 11	1430.4 MHz to 1450.4 MHz
	WCDMA band 12	700.4 MHz to 713.6 MHz
	WCDMA band 13	779.4 MHz to 784.6 MHz
	WCDMA band 14	790.4 MHz to 795.6 MHz
	WCDMA band S	2002.4 MHz to 2017.6 MHz
WCDMA band S170	2010 MHz to 2020 MHz	
WCDMA band S190	2000 MHz to 2010 MHz	

Statistics		
Statistical count		1 to 1000
Values		current, average, minimum/maximum, standard deviation

Trigger		
Trigger sources		BASE: external TRIG A, BASE: external TRIG B, GPRF: BB generator, WCDMA: free run, WCDMA: free run (fast sync), WCDMA: IF power, WCDMA: DCCH TTI trigger, WCDMA: frame trigger, WCDMA: HS-DPCCH trigger, WCDMA: slot trigger

Modulation analysis

Filter		3.84 MHz, RRC, $\alpha = 0.22$, WCDMA filter
Level range		-28 dBm to +42 dBm ¹²

¹² The maximum permissible continuous power is +34 dBm due to thermal limits.

Analysis modes	with the R&S®CMW-KM400 option	QPSK, WCDMA
	with the R&S®CMW-KM400 and R&S®CMW-KM401 options	WCDMA + HSDPA, WCDMA + HSUPA, WCDMA + HSPA
	with the R&S®CMW-KM400 and R&S®CMW-KM401 and R&S®CMW-KM403 options	WCDMA + HSPA+
Measured parameters	numeric results and standard deviation	error vector magnitude (EVM), magnitude error (ME), phase error (PE), frequency error, I/Q origin offset, I/Q imbalance, UE power, power steps, phase discontinuity, CDP, CDE
	graphical	EVM versus time, EVM versus chip, ME versus time, ME versus chip, PE versus time, PE versus chip, FE versus time, UE versus time, PS versus slot, PD versus slot, CDP versus slot, CDE versus slot, CD monitor

Error vector magnitude (EVM)		
Measurement range		up to 25 %, RMS
Inherent EVM		< 2.5 %, RMS
Measurement length		half-slot, 1 slot, multislot (1 to 120)

Frequency error		
Measurement range		±3 kHz
Frequency measurement uncertainty		< 20 Hz + drift of timebase, see general technical specifications

I/Q origin offset		
Inherent I/Q offset	for average ≥ 10 measurements	< -55 dB

I/Q imbalance		
Inherent I/Q imbalance		< -50 dB

Spectrum measurements

Adjacent channel leakage ratio		
Filter	RMS detector	3.84 MHz, RRC, $\alpha = 0.22$, WCDMA filter
Dynamic range	first adjacent channel at ±5 MHz	> 54 dB
	second adjacent channel at ±10 MHz	> 57 dB
Expected nominal power setting for full dynamic range	RF1 COM, RF2 COM	-4 dBm to +42 dBm ¹³
Uncertainty	for -33 dBc first adjacent channel level	< 0.5 dB
	for -43 dBc second adjacent channel level	< 0.5 dB
Measurement length		1 slot (2560 chip)

Power meter

UE power measurement		
Filter	RMS detector	bandpass, 6.3 MHz, RRC, $\alpha = 0.22$
Level range		-55 dBm to +42 dBm ¹³
Level uncertainty		see general technical specifications
Measurement length		half-slot, 1 slot

¹³ The maximum permissible continuous power is +34 dBm due to thermal limits.

Off power measurement	RMS detector	
Filter		3.84 MHz, RRC, $\alpha = 0.22$, WCDMA filter
Noise floor		-72 dBm
Level uncertainty		see general technical specifications + uncertainty due to noise floor

3G WCDMA signaling (prerequisite: R&S[®] CMW-KS400, R&S[®] CMW-B300A/R&S[®] CMW-B300B options; additionally R&S[®] CMW-KS410 and R&S[®] CMW-KS425 option)

Standard		3GPP FDD
Symbol rate		3.84 MHz

Channels		
Physical channels	DL	P-CPICH, P-SCH, S-SCH, P-CCPCH, S-CCPCH, AICH, PICH
	DL OCNS R99	16-channel orthogonal channel noise
	UL	DPCH, DPDCH, PRACH
Radio bearer	DPCH signaling radio bearer (SRB)	
	DL	1.7 kbps, 2.5 kbps, 3.4 kbps, 13.6 kbps
	UL	1.7 kbps, 2.5 kbps, 3.4 kbps, 13.6 kbps
	DPCH reference measurement channels (RMC) in line with 3GPP TS 34.121	
	DL	12.2 kbps, 64 kbps, 144 kbps, 384 kbps
	UL	12.2 kbps, 64 kbps, 144 kbps, 384 kbps
	DPCH voice echo NB-AMR	
	with the R&S [®] CMW-KS400 option	12.2 kbps
	with the R&S [®] CMW-KS400 and R&S [®] CMW-KS410 options	4.75 kbps, 5.15 kbps, 5.9 kbps, 6.7 kbps, 7.4 kbps, 7.95 kbps, 10.2 kbps, 12.2 kbps
	DPCH voice echo WB-AMR	
with the R&S [®] CMW-KS400 and R&S [®] CMW-KS410 options	6.6 kbps, 8.85 kbps, 12.65 kbps, 14.25 kbps, 15.85 kbps, 18.25 kbps, 19.85 kbps, 23.05 kbps, 23.85 kbps	
DPCH video echo		64 kbps

Frequency range		
Bands 1 to 14	with the R&S [®] CMW-KS400 option	
	DL	see WCDMA RF generator specifications
	UL	see WCDMA RF analyzer specifications
Band S, band S170, band S190	with the R&S [®] CMW-KS400 and R&S [®] CMW-KS425 options	
	DL	see WCDMA RF generator specifications
	UL	see WCDMA RF analyzer specifications

Frequency setting		channel number
--------------------------	--	----------------

Output level range	depending on PAR	see general technical specifications
Output level uncertainty		see general technical specifications
Output level resolution		see general technical specifications
Output level setting		total output power

Channel levels	P-CPICH, P-SCH, S-SCH, P-CCPCH, PICH, DPCH, OCNS	-30 dB to +0 dB relative to total power
-----------------------	--	---

Signal quality		
Error vector magnitude (EVM)	global EVM for DL RMC in line with 3GPP TS 34.121 C3.1 to C3.4 with DPCH/CPICH = 0 dB	< 2 %, RMS

LTE specifications – mobile station test ¹⁴

Standard	LTE FDD and TDD
----------	-----------------

LTE RF generator (prerequisite: R&S[®]CMW-B110A/R&S[®]CMW-B110D option)

Frequency range		
	E-UTRA band 1, FDD	2110 MHz to 2170 MHz
	E-UTRA band 2, FDD	1930 MHz to 1990 MHz
	E-UTRA band 3, FDD	1805 MHz to 1880 MHz
	E-UTRA band 4, FDD	2110 MHz to 2155 MHz
	E-UTRA band 5, FDD	869 MHz to 894 MHz
	E-UTRA band 6, FDD	875 MHz to 885 MHz
	E-UTRA band 7, FDD	2620 MHz to 2690 MHz
	E-UTRA band 8, FDD	925 MHz to 960 MHz
	E-UTRA band 9, FDD	1844.9 MHz to 1879.9 MHz
	E-UTRA band 10, FDD	2110 MHz to 2170 MHz
	E-UTRA band 11, FDD	1475.9 MHz to 1495.9 MHz
	E-UTRA band 12, FDD	729 MHz to 746 MHz
	E-UTRA band 13, FDD	746 MHz to 756 MHz
	E-UTRA band 14, FDD	758 MHz to 768 MHz
	E-UTRA band 15, FDD	2600 MHz to 2620 MHz
	E-UTRA band 16, FDD	2585 MHz to 2600 MHz
	E-UTRA band 17, FDD	734 MHz to 746 MHz
	E-UTRA band 18, FDD	860 MHz to 875 MHz
	E-UTRA band 19, FDD	875 MHz to 890 MHz
	E-UTRA band 20, FDD	791 MHz to 821 MHz
	E-UTRA band 21, FDD	1495.9 MHz to 1510.9 MHz
	E-UTRA band 22, FDD, prerequisite: R&S [®] CMW-KB036 option	3510 MHz to 3590 MHz
	E-UTRA band 23, FDD	2180 MHz to 2200 MHz
	E-UTRA band 24, FDD	1525 MHz to 1559 MHz
	E-UTRA band 25, FDD	1930 MHz to 1995 MHz
	E-UTRA band 26, FDD	859 MHz to 894 MHz
	E-UTRA band 27, FDD	852 MHz to 869 MHz
	E-UTRA band 28, FDD	758 MHz to 803 MHz
	E-UTRA band 29, FDD	717 MHz to 728 MHz
	E-UTRA band 30, FDD	2350 MHz to 2360 MHz
	E-UTRA band 31, FDD	462.5 MHz to 467.5 MHz
	E-UTRA band 33, TDD	1900 MHz to 1920 MHz
	E-UTRA band 34, TDD	2010 MHz to 2025 MHz
	E-UTRA band 35, TDD	1850 MHz to 1910 MHz
	E-UTRA band 36, TDD	1930 MHz to 1990 MHz
	E-UTRA band 37, TDD	1910 MHz to 1930 MHz
	E-UTRA band 38, TDD	2570 MHz to 2620 MHz
	E-UTRA band 39, TDD	1880 MHz to 1920 MHz
	E-UTRA band 40, TDD	2300 MHz to 2400 MHz
	E-UTRA band 41, TDD	2496 MHz to 2690 MHz
	E-UTRA band 42, TDD, prerequisite: R&S [®] CMW-KB036 option	3400 MHz to 3600 MHz
	E-UTRA band 43, TDD, prerequisite: R&S [®] CMW-KB036 option	3600 MHz to 3800 MHz
	E-UTRA band 44, TDD	703 MHz to 803 MHz

¹⁴ R&S[®]CMW500 and R&S[®]CMW280 only.

LTE WiniQSIM2™ (R&S® CMW-KW500 option)

Arbitrary waveform file	LTE FDD	LTE_FDD_QPSK_10MHZ.WV (PAR = 11.15 dB)
	LTE TDD	LTE_TDD_64QAM_20MHZ.WV (PAR = 11.10 dB)
Output level range	depending on PAR	see general technical specifications
Output level uncertainty	waveform file used: LTE_FDD_QPSK_10MHZ.WV	see general technical specifications
	waveform file used: LTE_TDD_64QAM_20MHZ.WV	see general technical specifications
Output level resolution		see general technical specifications
Signal quality		
Error vector magnitude (EVM)	EVM PDSCH QPSK, bandwidth = 10 MHz, 50 resource blocks, PRB symbol offset = 3, 10 subframes, PCFICH present, waveform file used: LTE_FDD_QPSK_10MHZ.WV	< 2 %, RMS
	EVM PDSCH 64QAM, bandwidth = 20 MHz, 100 resource blocks, PRB symbol offset = 2, uplink/downlink configuration 1, special subframe configuration 7, waveform file used: LTE_TDD_64QAM_20MHZ.WV	< 2 %, RMS

LTE FDD RF analyzer (R&S® CMW-KM500 option)

Bandwidth		1.4 MHz, 3 MHz, 5 MHz, 10 MHz, 15 MHz, 20 MHz
Frequency range	E-UTRA band 1, FDD	1920 MHz to 1980 MHz
	E-UTRA band 2, FDD	1850 MHz to 1910 MHz
	E-UTRA band 3, FDD	1710 MHz to 1785 MHz
	E-UTRA band 4, FDD	1710 MHz to 1755 MHz
	E-UTRA band 5, FDD	824 MHz to 849 MHz
	E-UTRA band 6, FDD	830 MHz to 840 MHz
	E-UTRA band 7, FDD	2500 MHz to 2570 MHz
	E-UTRA band 8, FDD	880 MHz to 915 MHz
	E-UTRA band 9, FDD	1749.9 MHz 1784.9 MHz
	E-UTRA band 10, FDD	1710 MHz to 1770 MHz
	E-UTRA band 11, FDD	1427.9 MHz to 1447.9 MHz
	E-UTRA band 12, FDD	699 MHz to 716 MHz
	E-UTRA band 13, FDD	777 MHz to 787 MHz
	E-UTRA band 14, FDD	788 MHz to 798 MHz
	E-UTRA band 15, FDD	1900 MHz to 1920 MHz
	E-UTRA band 16, FDD	2010 MHz to 2025 MHz
	E-UTRA band 17, FDD	704 MHz to 716 MHz
	E-UTRA band 18, FDD	815 MHz to 830 MHz
	E-UTRA band 19, FDD	830 MHz to 845 MHz
	E-UTRA band 20, FDD	832 MHz to 862 MHz
	E-UTRA band 21, FDD	1447.9 MHz to 1462.9 MHz
E-UTRA band 22, FDD, prerequisite: R&S®CMW-KB036 option	3410 MHz to 3490 MHz	
E-UTRA band 23, FDD	2000 MHz to 2020 MHz	
E-UTRA band 24, FDD	1625.5 MHz to 1660.5 MHz	
E-UTRA band 25, FDD	1850 MHz to 1915 MHz	
E-UTRA band 26, FDD	814 MHz to 849 MHz	
E-UTRA band 27, FDD	807 MHz to 824 MHz	
E-UTRA band 28, FDD	703 MHz to 748 MHz	
E-UTRA band 30, FDD	2305 MHz to 2315 MHz	
E-UTRA band 31, FDD	452.5 MHz to 457.5 MHz	
Level setting		manual mode

Statistics		
Statistical count		1 to 1000
Values		current, average, minimum/maximum, standard deviation

Trigger		
Trigger source		BASE: external TRIG A, BASE: external TRIG B, GPRF: BB generator, LTE: free run (fast sync), LTE: IF power

Power measurement

Slot power		
Level range	RMS detector	-50 dBm to +30 dBm, RMS
Level uncertainty		see general technical specifications

Modulation analysis

Measured parameters	numeric results	error vector magnitude (EVM), magnitude error (ME), phase error (PE), frequency error, I/Q origin offset, TX power, peak power, resource block power (RB power)
	graphical	EVM versus SC-FDMA symbol, ME versus SC-FDMA symbol, PE versus SC-FDMA symbol, EVM versus subcarrier, in-band emissions, spectrum flatness, I/Q constellation

Error vector magnitude (EVM)		
Inherent EVM	allocated resource blocks ≤ 15	
	-34 dBm \leq input level $<$ +30 dBm, RMS	$< 1 \%$, RMS
	-38 dBm \leq input level $<$ -34 dBm, RMS	$< 1.5 \%$, RMS
	allocated resource blocks ≤ 50	
	-30 dBm \leq input level \leq +30 dBm, RMS	$< 1 \%$, RMS
	-38 dBm \leq input level $<$ -30 dBm, RMS	$< 2 \%$, RMS
	allocated resource blocks ≤ 100	
	-28 dBm \leq input level \leq +30 dBm, RMS	$< 1 \%$, RMS
-38 dBm \leq input level $<$ -28 dBm, RMS	$< 2.5 \%$, RMS	

Frequency error		
Measurement range		± 80 kHz
Frequency measurement uncertainty		< 20 Hz ¹⁵ + drift of timebase, see general technical specifications

I/Q origin offset		
Inherent I/Q offset	for average ≥ 10 measurements	< -50 dB

In-band emissions		
Dynamic range	allocated resource blocks ≤ 50 , $f_{RF} < 3300$ MHz	> 50 dB
	allocated resource blocks ≤ 50 , $f_{RF} > 3300$ MHz	> 47 dB
Expected nominal power setting for full dynamic range	RF1 COM, RF2 COM	see general technical specifications

¹⁵ For frequency error measurements relative to the downlink signal of the same R&S®CMW500, the uncertainty is in line with 3GPP TS 36.521-1 V9.3.0.

Equalizer spectrum flatness	allocated resource blocks ≤ 50	
Level uncertainty		< 0.5 dB

Spectrum measurements

Adjacent channel leakage ratio		
Filter	E-UTRA	rectangle 1.08 MHz, 2.7 MHz, 4.5 MHz, 9 MHz, 13.5 MHz, 18 MHz
	UTRA	3.84 MHz, RRC, $\alpha = 0.22$, WCDMA filter
Dynamic range	E-UTRA, $f_{RF} < 3300$ MHz	> 45 dB
	E-UTRA, $f_{RF} > 3300$ MHz	> 42 dB
	UTRA, $f_{RF} < 3300$ MHz	> 52 dB
	UTRA, $f_{RF} > 3300$ MHz	> 49 dB
Expected nominal power setting for full dynamic range	RF1 COM, RF2 COM	see general technical specifications

Spectrum emission mask (SEM)		
Frequency span		70 MHz
Noise floor	<i>RBW</i> \rightarrow 1 MHz, $f_{RF} < 3300$ MHz	< -35 dBm
	<i>RBW</i> \rightarrow 1 MHz, $f_{RF} > 3300$ MHz	< -32 dBm
	<i>RBW</i> \rightarrow 100 kHz, $f_{RF} < 3300$ MHz	< -40 dBm
	<i>RBW</i> \rightarrow 100 kHz, $f_{RF} > 3300$ MHz	< -37 dBm
	<i>RBW</i> \rightarrow 30 kHz, $f_{RF} < 3300$ MHz	< -45 dBm
	<i>RBW</i> \rightarrow 30 kHz, $f_{RF} > 3300$ MHz	< -42 dBm

LTE FDD eNodeB RF analyzer (R&S®CMW-KN500 option)

Bandwidth		1.4 MHz, 3 MHz, 5 MHz, 10 MHz, 15 MHz, 20 MHz
------------------	--	---

Frequency range	E-UTRA band 1, FDD	2110 MHz to 2170 MHz
	E-UTRA band 2, FDD	1930 MHz to 1990 MHz
	E-UTRA band 3, FDD	1805 MHz to 1880 MHz
	E-UTRA band 4, FDD	2110 MHz to 2155 MHz
	E-UTRA band 5, FDD	869 MHz to 894 MHz
	E-UTRA band 6, FDD	875 MHz to 885 MHz
	E-UTRA band 7, FDD	2620 MHz to 2690 MHz
	E-UTRA band 8, FDD	925 MHz to 960 MHz
	E-UTRA band 9, FDD	1844.9 MHz to 1879.9 MHz
	E-UTRA band 10, FDD	2110 MHz to 2170 MHz
	E-UTRA band 11, FDD	1475.9 MHz to 1495.9 MHz
	E-UTRA band 12, FDD	729 MHz to 746 MHz
	E-UTRA band 13, FDD	746 MHz to 756 MHz
	E-UTRA band 14, FDD	758 MHz to 768 MHz
	E-UTRA band 15, FDD	2600 MHz to 2620 MHz
	E-UTRA band 16, FDD	2585 MHz to 2600 MHz
	E-UTRA band 17, FDD	734 MHz to 746 MHz
	E-UTRA band 18, FDD	860 MHz to 875 MHz
	E-UTRA band 19, FDD	875 MHz to 890 MHz
	E-UTRA band 20, FDD	791 MHz to 821 MHz
	E-UTRA band 21, FDD	1495.9 MHz to 1510.9 MHz
	E-UTRA band 22, FDD, prerequisite: R&S®CMW-KB036 option	3510 MHz to 3590 MHz
	E-UTRA band 23, FDD	2180 MHz to 2200 MHz
	E-UTRA band 24, FDD	1525 MHz to 1559 MHz
	E-UTRA band 25, FDD	1930 MHz to 1995 MHz
	E-UTRA band 26, FDD	859 MHz to 894 MHz
	E-UTRA band 27, FDD	852 MHz to 869 MHz
	E-UTRA band 28, FDD	758 MHz to 803 MHz
	E-UTRA band 29, FDD	717 MHz to 728 MHz
	E-UTRA band 30, FDD	2350 MHz to 2360 MHz
	E-UTRA band 31, FDD	462.5 MHz to 467.5 MHz
Level setting		manual mode

Statistics		
Statistical count		1 to 1000
Values		current, average, minimum/maximum, standard deviation

Trigger		
Trigger source		BASE: external TRIG A, BASE: external TRIG B, GPRF: BB generator, LTE: free run (fast sync), LTE: IF power

Power measurement

Slot power		
Level range	RMS detector	-50 dBm to +30 dBm, RMS
Level uncertainty		see general technical specifications

Modulation analysis

Measured parameters	numeric results	error vector magnitude (EVM), magnitude error (ME), phase error (PE), frequency error, I/Q origin offset, TX power, peak power, reference symbol power, OFDM symbol power
	graphical	EVM versus OFDMA symbol, ME versus OFDMA symbol, PE versus OFDMA symbol, OFDM symbol power spectrum flatness, spectrum ACLR I/Q constellation

Error vector magnitude (EVM)		
Inherent EVM	for average ≥ 10 subframes -20 dBm \leq input level < +30 dBm, RMS	< 1.5 %, RMS

Frequency error		
Measurement range		± 80 kHz
Frequency measurement uncertainty		< 20 Hz ¹⁶ + drift of timebase, see general technical specifications

Spectrum measurements

Adjacent channel leakage ratio		
Filter	E-UTRA	rectangle 1.08 MHz, 2.7 MHz, 4.5 MHz, 9 MHz, 13.5 MHz, 18 MHz
	UTRA	1.28 MHz, RRC, $\alpha = 0.22$, WCDMA filter 3.84 MHz, RRC, $\alpha = 0.22$, WCDMA filter 7.68 MHz, RRC, $\alpha = 0.22$, WCDMA filter
Dynamic range	E-UTRA, $f_{RF} < 3300$ MHz	> 50 dB
	E-UTRA, $f_{RF} > 3300$ MHz	> 48 dB
	UTRA, $f_{RF} < 3300$ MHz	> 52 dB
	UTRA, $f_{RF} > 3300$ MHz	> 52 dB
Expected nominal power setting for full dynamic range	RF1 COM, RF2 COM	see general technical specifications

¹⁶ For frequency error measurements relative to the downlink signal of the same R&S®CMW500, the uncertainty is in line with 3GPP TS 36.521-1 V9.3.0.

Spectrum emission mask (SEM)		
Frequency span		70 MHz
Noise floor	$RBW \rightarrow \leq 1 \text{ MHz}$, expected nominal power < 12 dBm, $f_{RF} < 3300 \text{ MHz}$	< -58 dBm
	$RBW \rightarrow \leq 1 \text{ MHz}$, expected nominal power < 12 dBm, $f_{RF} > 3300 \text{ MHz}$	< -55 dBm

LTE FDD signaling (prerequisite: R&S®CMW-KS500, R&S®CMW-B300A/R&S®CMW-B300B options) ¹⁷

Standard		3GPP E-UTRA FDD
-----------------	--	-----------------

Channels		
Physical channels and signals	DL	RS (cell-specific RS), PSS, SSS, PBCH, PCFICH, PHICH, PDCCH, PDSCH
	UL	RS (demodulation RS), PRACH, PUCCH, PUSCH
Bandwidth		1.4 MHz, 3 MHz, 5 MHz, 10 MHz, 15 MHz, 20 MHz
Modulation schemes	DL PDSCH	QPSK, 16QAM, 64QAM
	UL PUSCH	QPSK, 16QAM

Reference measurement channels	RMCs in line with 3GPP TS 36.521 Annex A.2 (UL) and Annex A.3 (DL)	RMCs for FDD, full and partial RB allocation, modulation: QPSK, 16QAM, 64QAM (DL only)
--------------------------------	--	--

Frequency range		
Bands 1 to 31	with the R&S®CMW-KS500 option	
	DL	see LTE FDD RF generator specifications
	UL	see LTE FDD RF analyzer specifications

Frequency setting		channel number
--------------------------	--	----------------

DL signal

Output level range	due to PAR	15 dB below max. output level of RF generator, see general technical specifications
Output level uncertainty		see general technical specifications
Output level resolution		0.1 dB
Output level setting	in line with 3GPP TS 36.521 Annex C.0	RS energy per resource element (EPRE) [dBm/15 kHz]

Channel levels	PSS, SSS, PBCH, PCFICH, PHICH, PDCCH, PDSCH	-30 dB to +0 dB relative to RS EPRE
	PHICH	-30 dB to -12 dB relative to RS EPRE

Signal quality		
Error vector magnitude (EVM)	global EVM for cell with bandwidth = 20 MHz	< 2 %, RMS

¹⁷ R&S®CMW500 and R&S®CMW280 only.

LTE TDD RF analyzer (R&S®CMW-KM550 option)

Bandwidth		1.4 MHz, 3 MHz, 5 MHz, 10 MHz, 15 MHz, 20 MHz
Frequency range	E-UTRA band 33, TDD	1900 MHz to 1920 MHz
	E-UTRA band 34, TDD	2010 MHz to 2025 MHz
	E-UTRA band 35, TDD	1850 MHz to 1910 MHz
	E-UTRA band 36, TDD	1930 MHz to 1990 MHz
	E-UTRA band 37, TDD	1910 MHz to 1930 MHz
	E-UTRA band 38, TDD	2570 MHz to 2620 MHz
	E-UTRA band 39, TDD	1880 MHz to 1920 MHz
	E-UTRA band 40, TDD	2300 MHz to 2400 MHz
	E-UTRA band 41, TDD	2496 MHz to 2690 MHz
	E-UTRA band 42, TDD, prerequisite: R&S®CMW-KB036 option	3400 MHz to 3600 MHz
	E-UTRA band 43, TDD, prerequisite: R&S®CMW-KB036 option	3600 MHz to 3800 MHz
Level setting	E-UTRA band 44, TDD	703 MHz to 803 MHz manual mode
Statistics		
Statistical count		1 to 1000
Values		current, average, minimum/maximum, standard deviation
Trigger		
Trigger source		BASE: external TRIG A, BASE: external TRIG B, GPRF: BB generator, LTE: free run (fast sync), LTE: IF power

Power measurement

Slot power	RMS detector	
Level range		-50 dBm to +30 dBm, RMS
Level uncertainty		see general technical specifications

Modulation analysis

Measured parameters	numeric results	error vector magnitude (EVM), magnitude error (ME), phase error (PE), frequency error, I/Q origin offset, TX power, peak power, resource block power (RB power)
	graphical	EVM versus SC-FDMA symbol, ME versus SC-FDMA symbol, PE versus SC-FDMA symbol, EVM versus subcarrier, in-band emissions, spectrum flatness, I/Q constellation

Error vector magnitude (EVM)		
Inherent EVM	allocated resource blocks ≤ 15	
	-34 dBm \leq input level $< +30$ dBm, RMS	< 1 %, RMS
	-38 dBm \leq input level < -34 dBm, RMS	< 1.5 %, RMS
	allocated resource blocks ≤ 50	
	-30 dBm \leq input level $\leq +30$ dBm, RMS	< 1 %, RMS
	-38 dBm \leq input level < -30 dBm, RMS	< 2 %, RMS
	allocated resource blocks ≤ 100	
-28 dBm \leq input level $\leq +30$ dBm, RMS	< 1 %, RMS	
-38 dBm \leq input level < -28 dBm, RMS	< 2.5 %, RMS	

Frequency error		
Measurement range		± 80 kHz
Frequency measurement uncertainty		< 20 Hz ¹⁸ + drift of timebase, see general technical specifications

I/Q origin offset		
Inherent I/Q offset		< -50 dB

In-band emissions		
Dynamic range	allocated resource blocks ≤ 50 , $f_{RF} < 3300$ MHz	> 50 dB
	allocated resource blocks ≤ 50 , $f_{RF} > 3300$ MHz	> 47 dB
Expected nominal power setting for full dynamic range	RF1 COM, RF2 COM	see general technical specifications

Equalizer spectrum flatness		
Level uncertainty	allocated resource blocks ≤ 50	< 0.5 dB

Spectrum measurements

Adjacent channel leakage ratio		
Filter	E-UTRA	rectangle 1.08 MHz, 2.7 MHz, 4.5 MHz, 9 MHz, 13.5 MHz, 18 MHz
	UTRA	1.28 MHz, RRC, $\alpha = 0.22$, WCDMA filter
Dynamic range	E-UTRA, $f_{RF} < 3300$ MHz	> 45 dB
	E-UTRA, $f_{RF} > 3300$ MHz	> 42 dB
	UTRA, $f_{RF} < 3300$ MHz	> 56 dB
	UTRA, $f_{RF} > 3300$ MHz	> 53 dB
Expected nominal power setting for full dynamic range	RF1 COM, RF2 COM	see general technical specifications

Spectrum emission mask (SEM)		
Frequency span		70 MHz
Noise floor	<i>RBW</i> $\rightarrow 1$ MHz, $f_{RF} < 3300$ MHz	< -35 dBm
	<i>RBW</i> $\rightarrow 1$ MHz, $f_{RF} > 3300$ MHz	< -32 dBm
	<i>RBW</i> $\rightarrow 100$ kHz, $f_{RF} < 3300$ MHz	< -40 dBm
	<i>RBW</i> $\rightarrow 100$ kHz, $f_{RF} > 3300$ MHz	< -37 dBm
	<i>RBW</i> $\rightarrow 30$ kHz, $f_{RF} < 3300$ MHz	< -45 dBm
	<i>RBW</i> $\rightarrow 30$ kHz, $f_{RF} > 3300$ MHz	< -42 dBm

¹⁸ For frequency error measurements relative to the downlink signal of the same R&S[®]CMW500, the uncertainty is in line with 3GPP TS 36.521-1 V9.3.0.

LTE TDD eNodeB RF analyzer (R&S®CMW-KN550 option)

Bandwidth		1.4 MHz, 3 MHz, 5 MHz, 10 MHz, 15 MHz, 20 MHz
Frequency range	E-UTRA band 33, TDD	1900 MHz to 1920 MHz
	E-UTRA band 34, TDD	2010 MHz to 2025 MHz
	E-UTRA band 35, TDD	1850 MHz to 1910 MHz
	E-UTRA band 36, TDD	1930 MHz to 1990 MHz
	E-UTRA band 37, TDD	1910 MHz to 1930 MHz
	E-UTRA band 38, TDD	2570 MHz to 2620 MHz
	E-UTRA band 39, TDD	1880 MHz to 1920 MHz
	E-UTRA band 40, TDD	2300 MHz to 2400 MHz
	E-UTRA band 41, TDD	2496 MHz to 2690 MHz
	E-UTRA band 42, TDD, prerequisite: R&S®CMW-KB036 option	3400 MHz to 3600 MHz
E-UTRA band 43, TDD, prerequisite: R&S®CMW-KB036 option	3600 MHz to 3800 MHz	
E-UTRA band 44, TDD	703 MHz to 803 MHz	
Level setting		manual mode
Statistics		
Statistical count		1 to 1000
Values		current, average, minimum/maximum, standard deviation
Trigger		
Trigger source		BASE: external TRIG A, BASE: external TRIG B, GPRF: BB generator, LTE: free run (fast sync), LTE: IF power

Power measurement

Slot power	RMS detector	
Level range		-50 dBm to +30 dBm, RMS
Level uncertainty		see general technical specifications

Modulation analysis

Measured parameters	numeric results	error vector magnitude (EVM), magnitude error (ME), phase error (PE), frequency error, I/Q origin offset, TX power, peak power, reference symbol power, OFDM symbol power
	graphical	EVM versus OFDMA symbol, ME versus OFDMA symbol, PE versus OFDMA symbol, OFDM symbol power spectrum flatness, spectrum ACLR, I/Q constellation
Error vector magnitude (EVM)		
Inherent EVM	for average ≥ 10 subframes -20 dBm \leq input level < +30 dBm, RMS	< 1.5 %, RMS

Frequency error		
Measurement range		±80 kHz
Frequency measurement uncertainty		< 20 Hz ¹⁹ + drift of timebase, see general technical specifications

Spectrum measurements

Adjacent channel leakage ratio		
Filter	E-UTRA	rectangle 1.08 MHz, 2.7 MHz, 4.5 MHz, 9 MHz, 13.5 MHz, 18 MHz
	UTRA	1.28 MHz, RRC, $\alpha = 0.22$, WCDMA filter 3.84 MHz, RRC, $\alpha = 0.22$, WCDMA filter 7.68 MHz, RRC, $\alpha = 0.22$, WCDMA filter
Dynamic range	E-UTRA, $f_{RF} < 3300$ MHz	> 50 dB
	E-UTRA, $f_{RF} > 3300$ MHz	> 47 dB
	UTRA128, $f_{RF} < 3300$ MHz	> 52 dB
	UTRA384, $f_{RF} < 3300$ MHz	> 52 dB
	UTRA768, $f_{RF} < 3300$ MHz	> 49 dB
	UTRA128, $f_{RF} > 3300$ MHz	> 52 dB
	UTRA384_1, $f_{RF} > 3300$ MHz	> 50 dB
	UTRA384_2, $f_{RF} > 3300$ MHz	> 52 dB
UTRA768, $f_{RF} > 3300$ MHz	> 49 dB	
Expected nominal power setting for full dynamic range	RF1 COM, RF2 COM	see general technical specifications

Spectrum emission mask (SEM)		
Frequency span		70 MHz
Noise floor	$RBW \rightarrow \leq 1$ MHz, expected nominal power < 12dBm, $f_{RF} < 3300$ MHz	< -58 dBm
	$RBW \rightarrow \leq 1$ MHz, expected nominal power < 12dBm, $f_{RF} > 3300$ MHz	< -55 dBm

¹⁹ For frequency error measurements relative to the downlink signal of the same R&S®CMW500, the uncertainty is in line with 3GPP TS 36.521-1 V9.3.0.

Bluetooth® specifications

Standard	standard	Bluetooth® Core Specification Version 2.1 + EDR, Version 4.0 + LE
	test standard	Radio Frequency Test Specification V1.2/V2.0/V2.0+EDR/V2.1/V2.1+EDR, Bluetooth® Low Energy RF PHY Test Specification, RF-PHY.TS/4.0.1

Bluetooth® RF generator (prerequisite: R&S®CMW-B110A/R&S®CMW-B110D option)

Frequency range	Bluetooth®	2402 MHz to 2480 MHz
------------------------	------------	----------------------

Bluetooth® WinIQSIM2™ (R&S®CMW-KW610 option)

Arbitrary waveform file	basic rate	BLUETOOTH_11110000_DH5.WV LAP: 123456, (PAR = 0.00 dB)
	enhanced data rate (EDR)	BLUETOOTH_PRBS9_3-DH5.WV LAP: 123456, (PAR = 3.20 dB)

Output level range	depending on PAR	see general technical specifications
Output level uncertainty	waveform files used: BLUETOOTH_11110000_DH5.WV, BLUETOOTH_PRBS_3-DH5.WV	see general technical specifications
Output level resolution		see general technical specifications

Signal quality		
Modulation index uncertainty	basic rate, frequency deviation Δf_1 max. = 160 kHz, waveform file used: BLUETOOTH_11110000_DH5.WV	< 1 %
Differential error vector magnitude (DEV M)	enhanced data rate, waveform file used: BLUETOOTH_PRBS9_3-DH5.WV	< 1.5 %, RMS

Bluetooth® RF analyzer (R&S®CMW-KM610 option)

Frequency range	Bluetooth®	2402 MHz to 2480 MHz
------------------------	------------	----------------------

Statistics		
Statistical count		1 to 1000
Values		current, average, maximum, minimum, standard deviation

Trigger		
Trigger sources		BT: IF power

Modulation analysis

Filter	<i>filter bandwidth</i> → wide	bandpass 2.0 MHz
	<i>filter bandwidth</i> → narrow	bandpass 1.3 MHz
Level range		-35 dBm to +42 dBm ²⁰
Supported packet types	basic rate	DH1, DH3, DH5
	enhanced data rate (EDR)	2-DH1, 2-DH3, 2-DH5, 3-DH1, 3-DH3, 3-DH5
Measured parameters	basic rate, numeric results and standard deviation	Δf_2 99.9 %, frequency accuracy, frequency drift, maximum drift rate, frequency deviation Δf_1 average, frequency deviation Δf_1 minimum, frequency deviation Δf_1 maximum, frequency deviation Δf_2 average, frequency deviation Δf_2 minimum, frequency deviation Δf_2 maximum, nominal power
Measured parameters	enhanced data rate (EDR), numeric results and standard deviation	99 % DEVM, frequency stability ω_i , frequency stability $(\omega_o + \omega_i)_{max}$, frequency stability $\omega_{o,max}$, RMS DEVM, peak RMS, nominal power
Total measurement range for frequency accuracy, frequency deviation and frequency drift	basic rate	±250 kHz
Frequency accuracy	basic rate	
Measurement range	for nominal deviation of 160 kHz	±100 kHz
Uncertainty	for deviation ≤ 160 kHz	< 2 kHz
Frequency deviation average	basic rate	
Measurement range	without frequency offset	≤ 210 kHz
Uncertainty	for modulation index 0.22 to 0.42	< 1 %
Frequency drift	basic rate	
Measurement range		±50 kHz
Uncertainty	measured in burst related to frequency offset in preamble, with 10101010 pattern	< 2 kHz
Frequency stability ω_i	enhanced data rate	
Measurement range		±100 kHz
Uncertainty	for ω_i ≤ 75 kHz, for deviation ≤ 160 kHz	< 2 kHz
Frequency stability $\omega_{o,max}$	enhanced data rate	
Measurement range		±15 kHz
Uncertainty	for ω_o ≤ 10 kHz	< 1 kHz
Differential error vector magnitude (DEVm)	enhanced data rate	
Inherent DEVm	for PRBS pattern	< 1.5 %, RMS < 3.0 %, peak

²⁰ The maximum permissible continuous power is +34 dBm due to thermal limits.

Bluetooth® signaling (prerequisite: R&S®CMW-KS600, R&S®CMW-KS610)

Standard		Bluetooth® Core Specification Version 2.1 + EDR Version 4.0 + LE
Frequency range	Bluetooth®	2402 MHz to 2480 MHz
Output level range	depending on PAR	see general technical specifications
Output level uncertainty		see general technical specifications
Output level resolution		see general technical specifications
GFSK modulation		
Modulation index uncertainty	basic rate, 11110000 pattern, 160 kHz frequency deviation	< 1 %
DPSK modulation		
Modulation uncertainty (DEVM)	enhanced data rate	< 1.5 %, RMS
Dirty Tx	prerequisite: R&S®CMW-KS610	
Drift uncertainty (basic rate)		< 0.5kHz
Drift uncertainty (EDR)		< 0.5kHz
Symbol time error uncertainty		same as timebase, see general technical specifications
Input level range	basic rate, enhanced data rate	-60 dBm to +42 dBm ²¹

²¹ The maximum permissible continuous power is +34 dBm due to thermal limits.

Bluetooth® RF analyzer (R&S® CMW-KM611 option)

Frequency range	Bluetooth®	2402 MHz to 2480 MHz
Statistics		
Statistical count		1 to 1000
Values		current, average, maximum, minimum, standard deviation
Trigger		
Trigger sources		BT: IF power

Modulation analysis

Filter	<i>filter bandwidth → wide</i>	bandpass 2.0 MHz
	<i>filter bandwidth → narrow</i>	bandpass 1.3 MHz
Level range		-100 dBm to +42 dBm ²²
Supported packet types		RF PHY Test Reference Packets
Measured parameters	numeric results and standard deviation	Δf2 99.9%, frequency accuracy, frequency offset, initial frequency drift, frequency drift, max drift rate, frequency deviation Δf1 average, frequency deviation Δf1 minimum, frequency deviation Δf1 maximum, frequency deviation Δf2 average, frequency deviation Δf2 minimum, frequency deviation Δf2 maximum, nominal power
Total measurement range for frequency accuracy, offset, deviation and drift measurements		±350 kHz
Frequency accuracy (using preamble)		
Measurement range	for nominal deviation of 250 kHz	±175 kHz
Uncertainty	for deviation ≤ 250 kHz	< 2 kHz
Frequency offset		
Measurement range	for nominal deviation of 250 kHz	±175 kHz
Uncertainty	for deviation ≤ 250 kHz	< 2 kHz
Frequency deviation average		
Measurement range	without frequency offset	≤ 350 kHz
Uncertainty	for modulation index 0.40 to 0.60	< 1.0 %
Initial frequency drift		
Measurement range		±75 kHz
Uncertainty	measured in burst related to frequency offset in preamble, with 10101010 pattern	< 2 kHz
Frequency drift		
Measurement range		±75 kHz
Uncertainty	measured in burst related to frequency offset in preamble, with 10101010 pattern	< 2 kHz

²² The maximum permissible continuous power is +34 dBm due to thermal limits.

GPS specifications

Standard		GPS
----------	--	-----

GPS RF generator (prerequisite: R&S®CMW-B110A/R&S®CMW-B110D option)

Frequency range	GPS band	
	L1	1575.42 MHz
	L2	1227.6 MHz

GPS WinIQSIM2™ (R&S®CMW-KW620 option)

Arbitrary waveform file		GPS_DEFAULT.WV (PAR = 3.66 dB)
Output level range	depending on PAR	see general technical specifications
Output level uncertainty	waveform file used: GPS_DEFAULT.WV	see general technical specifications
Output level resolution		see general technical specifications

DVB specifications

Standard		DVB-T
----------	--	-------

DVB RF generator (prerequisite: R&S®CMW-B110A/R&S®CMW-B110D option)

Frequency range	VHF band III	
	channels 5 to 12	174 MHz to 230 MHz
	UHF band IV	
	channels 21 to 34	470 MHz to 582 MHz
UHF band V		
	channels 35 to 69	582 MHz to 862 MHz

DVB WinIQSIM2™ (R&S®CMW-KW630 option)

Arbitrary waveform file		DVB-T_SCRAMBLED_16QAM_3SEC_TESTFILE.WV (PAR = 13.23 dB)
Output level range	depending on PAR	see general technical specifications
Output level uncertainty	waveform file used: DVB-T_SCRAMBLED_16QAM_3SEC_TESTFILE.WV	see general technical specifications
Output level resolution		see general technical specifications

FM STEREO RADIO specifications

Standard		FM STEREO RADIO
----------	--	-----------------

FM STEREO RADIO generator (prerequisite: R&S® CMW-B110A/R&S® CMW-B110D option)

Frequency range	FM	70 MHz to 110 MHz
-----------------	----	-------------------

FM STEREO RADIO waveforms (R&S® CMW-KV645 option)

Arbitrary waveform file		FM_M_M1K0_D75K0.WV (PAR = 0.00 dB)
-------------------------	--	---------------------------------------

Output level range	depending on PAR	see general technical specifications
Output level uncertainty	waveform file used: FM_M_M1K0_D75K0.WV	see general technical specifications
Output level resolution		see general technical specifications
Signal quality	RMS detector *SQRT(2)	
Deviation error	waveform file used: FM_M_M1K0_D75K0.WV	< 1 %

FM STEREO RADIO analyzer (R&S® CMW-KM645 option)

Frequency range	FM	70 MHz to 110 MHz
-----------------	----	-------------------

Statistics		
Statistical count		1 to 1000
Values		current, average, maximum, minimum, standard deviation

Audio filter, weighting

Lowpass		off, 3 kHz, 4 kHz, 15 kHz
Highpass		off, 6 Hz, 50 Hz, 300 Hz
Deemphasis		off, 50 µs, 75 µs, 750 µs
Weighting filter		off, A-weighting

RF carrier analysis

Carrier frequency error		
Measurement range	for nominal deviation of 75 kHz	±10 kHz
Uncertainty	for deviation ≤ 75 kHz	< 35 Hz + drift of timebase, see general technical specifications

Multiplex deviation		
Measurement range	without frequency offset	≤ 96 kHz
Uncertainty		< 1 %, peak

Modulation analysis

Filter	filter bandwidth	bandpass 500 kHz
Level range		-28 dBm to +42 dBm ²³
Measured parameters	numeric results	carrier power, carrier frequency error, multiplex deviation, pilot deviation, audio left/right deviation, pilot frequency error, THD left/right, THD+N/SINAD left/right, SNR left/right

²³ The maximum permissible continuous power is +34 dBm due to thermal limits.

Pilot frequency error		
Measurement range	for nominal deviation of 6.75 kHz	±10 Hz
Uncertainty	for deviation ≤ 67.5 kHz, drift of timebase according to pilot 19.0 kHz	< 0.1 Hz + drift of timebase, see general technical specifications

THD		
Measurement range		< 10 %
Inherent distortion		< 0.05 %
Uncertainty	for modulation frequency of 1 kHz and deviation of 67.5 kHz	< 1 % + inherent distortion

THD+N / (SINAD)		
Measurement range		< 10 %
Inherent distortion	with deemphasis filter (50 µs) and A-weighted filter	< 0.20 %
Uncertainty	for modulation frequency of 1 kHz, deviation of 67.5 kHz and with deemphasis filter (50 µs) and A-weighted filter	< 1 % + inherent distortion

SNR		
Inherent distortion	with deemphasis filter (50 µs) and A-weighted filter	> 54 dB

WLAN specifications

Standard		IEEE 802.11a, IEEE 802.11b, IEEE 802.11g, IEEE 802.11n, IEEE 802.11ac
-----------------	--	---

WLAN RF generator (prerequisite: R&S®CMW-B110A/R&S®CMW-B110D option)

Frequency range	WLAN IEEE 802.11b/g/n (2.4 GHz band)	2412 MHz to 2484 MHz
	WLAN IEEE 802.11a/n (5 GHz band), prerequisite: R&S®CMW-KB036 option	5000 MHz to 6000 MHz

WLAN ABG WinIQSIM2™ (R&S®CMW-KW650 option)

Arbitrary waveform files	in line with IEEE 802.11a/g OFDM 64QAM	WLAN_A_G_OFDM_64QAM.WV (PAR = 10.01 dB)
	in line with IEEE 802.11b CCK DQPSK	WLAN_B_CCK_DQPSK.WV (PAR = 1.48 dB)

Output level range	depending on PAR	see general technical specifications
Output level uncertainty	waveform files used: WLAN_A_G_OFDM_64QAM.WV, WLAN_B_CCK_DQPSK.WV	see general technical specifications
Output level resolution		see general technical specifications

Signal quality		
Error vector magnitude (EVM)	IEEE 802.11a/g, EVM all carriers, waveform file used: WLAN_A_G_OFDM_64QAM.WV	< -40 dB, RMS
	IEEE 802.11b, EVM, waveform file used: WLAN_B_CCK_DQPSK.WV	< 4 %, peak

WLAN N WinIQSIM2™ (R&S® CMW-KW651 option)

Arbitrary waveform files	in line with IEEE 802.11n 64QAM, code rate 5/6	WLAN_N_64QAM_5_6.WV (PAR = 10.01 dB)
Output level range	depending on PAR	see general technical specifications
Output level uncertainty	waveform files used: WLAN_N_64QAM_5_6.WV	see general technical specifications
Output level resolution		see general technical specifications
Signal quality		
Error vector magnitude (EVM)	IEEE 802.11n, EVM all carriers, waveform file used: WLAN_N_64QAM_5_6.WV	< -40 dB, RMS

WLAN AC WinIQSIM2™ (R&S® CMW-KW656 option)

Arbitrary waveform files	in line with IEEE 802.11ac 256QAM, 20 MHz, code rate 3/4	WLAN_VHT_BW20_MCS8_LEN4096.WV (PAR = 9.57 dB)
	in line with IEEE 802.11ac 256QAM, 40 MHz, code rate 3/4	WLAN_VHT_BW40_MCS8_LEN4096.WV (PAR = 11.22534 dB)
	in line with IEEE 802.11ac 256QAM, 80 MHz, code rate 3/4	WLAN_VHT_BW80_MCS8_LEN4096.WV (PAR = 10.23565 dB)
Output level range	depending on PAR	see general technical specifications
Output level uncertainty	waveform files used: WLAN_VHT_BW20_MCS8_LEN4096.WV WLAN_VHT_BW40_MCS8_LEN4096.WV WLAN_VHT_BW80_MCS8_LEN4096.WV	see general technical specifications
Output level resolution		see general technical specifications
Signal quality		
Error vector magnitude (EVM)	IEEE 802.11ac, EVM all carriers, waveform file used: WLAN_VHT_BW20_MCS8_LEN4096.WV	< -40 dB, RMS
	WLAN_VHT_BW40_MCS8_LEN4096.WV	< -40 dB, RMS
	WLAN_VHT_BW80_MCS8_LEN4096.WV	< -37 dB, RMS

WLAN ABG RF analyzer (R&S® CMW-KM650 option)

Frequency range	WLAN IEEE 802.11b/g	2412 MHz to 2484 MHz
	WLAN IEEE 802.11a, prerequisite: R&S® CMW-KB036 option	5000 MHz to 6000 MHz, for frequency exceptions for inherent spurious response, see general technical specifications
Statistics		
Statistical count		1 to 1000
Values		current, average, maximum, standard deviation
Trigger		
Trigger sources		WLAN: free run, WLAN: IF power

Modulation analysis

Filter		20 MHz
Level range		-28 dBm to +42 dBm ²⁴
Payload length		≥ 16 symbol
Analysis modes	DSSS	1 Mbps DBPSK, 2 Mbps DQPSK, 5.5 Mbps CCK, 11 Mbps CCK
	OFDM	6 Mbps BPSK, 9 Mbps BPSK, 12 Mbps QPSK, 18 Mbps QPSK, 24 Mbps 16QAM, 36 Mbps 16QAM, 48 Mbps 64QAM, 54 Mbps 64QAM
Measured parameters	DSSS, numeric results and standard deviation	burst power, error vector magnitude (EVM) peak, error vector magnitude (EVM) RMS, center frequency error, chip clock error, I/Q offset, gain imbalance, quadrature error
	DSSS, graphical	EVM versus chip, I/Q constellation
	OFDM, numeric results and standard deviation	burst power, EVM all carriers, EVM data carriers, EVM pilot carriers, center frequency error, symbol clock error, I/Q offset, gain imbalance, quadrature error
	OFDM, graphical	EVM versus symbol, EVM versus carrier, I/Q constellation, spectrum flatness
Error vector magnitude (EVM)		
Inherent EVM ²⁵	DSSS, IEEE 802.11b/g	< 5 %, peak < 2 %, RMS
	OFDM, IEEE 802.11g	< -40 dB, RMS
	OFDM, IEEE 802.11a	
	-18 dBm ≤ input level ≤ +42 dBm ²⁴ , RMS	< -40 dB, RMS ²⁶
Measurement length	DSSS	1000 samples
	OFDM	entire PPDU
Center frequency error		
Frequency measurement uncertainty	DSSS, IEEE 802.11b/g	< 20 Hz + drift of timebase, see general technical specifications
	OFDM, IEEE 802.11g, for ≥ 100 symbol (400 μs)	< 20 Hz + drift of timebase, see general technical specifications
	OFDM, IEEE 802.11a, for ≥ 100 symbol (400 μs)	< 35 Hz + drift of timebase, see general technical specifications
Chip clock error		
Uncertainty	DSSS	< 1 ppm

²⁴ The maximum permissible continuous power is +34 dBm due to thermal limits.

²⁵ Measured with channel estimation based on payload.

²⁶ 3 dB less with R&S®CMW-H590D RF frontend (ADV.).

Symbol clock error	OFDM	
Uncertainty		< 1 ppm
I/Q offset		
Inherent I/Q offset	DSSS, for average ≥ 10 measurements	< -50 dB
	OFDM, for average ≥ 10 measurements	< -45 dB
Spectrum flatness		
Level uncertainty	OFDM, IEEE 802.11g (2.4 GHz band)	< 0.5 dB
	OFDM, IEEE 802.11a (5 GHz band)	< 0.8 dB

Spectrum measurements

Transmit spectrum mask		
Frequency span		80 MHz
Dynamic range	DSSS	in line with IEEE 802.11b
	OFDM	in line with IEEE 802.11a/g
Expected nominal power setting for full dynamic range	RF1 COM, RF2 COM	
	IEEE 802.11g (2.4 GHz band)	+2 dBm to +42 dBm ²⁷
	IEEE 802.11a (5 GHz band)	+12 dBm to +42 dBm ²⁷

WLAN N RF analyzer (R&S®CMW-KM651 option)

Frequency range	WLAN IEEE 802.11n (2.4 GHz band) WLAN IEEE 802.11n (5 GHz band), prerequisite: R&S®CMW-KB036 option	2412 MHz to 2484 MHz 5000 MHz to 6000 MHz, for frequency exceptions for inherent spurious response, see general technical specifications
Statistics		
Statistical count		1 to 1000
Values		current, average, maximum, standard deviation
Trigger		
Trigger sources		WLAN: free run, WLAN: IF power
High throughput (HT)		
PPDU format		legacy mode, mixed mode, greenfield mode

Modulation analysis

Bandwidth		20 MHz, 40 MHz
Level range		-28 dBm to +42 dBm ²⁷
Payload length		≥ 16 symbol
Analysis modes		BPSK code rate 1/2 (MCS0), BPSK code rate 3/4, QPSK code rate 1/2 (MCS1), QPSK code rate 3/4 (MCS2), 16QAM code rate 1/2 (MCS3), 16QAM code rate 3/4 (MCS4), 64QAM code rate 1/2, 64QAM code rate 2/3 (MCS5), 64QAM code rate 3/4 (MCS6), 64QAM code rate 5/6 (MCS7)
	for optional 40 MHz MCS format	BPSK code rate 1/2 (MCS32)

²⁷ The maximum permissible continuous power is +34 dBm due to thermal limits.

Measured parameters	numeric results and standard deviation	burst power, EVM all carriers, EVM data carriers, EVM pilot carriers, center frequency error, symbol clock error, I/Q offset, gain imbalance, quadrature error
	graphical	EVM versus symbol, EVM versus carrier, spectrum flatness

Error vector magnitude (EVM)		
Inherent EVM ²⁸	IEEE 802.11n (2.4 GHz band) –28 dBm ≤ input level ≤ +42 dBm ²⁹ , RMS	< –40 dB, RMS ³⁰
	IEEE 802.11n (5 GHz band) –18 dBm ≤ input level ≤ +42 dBm ²⁹ , RMS	< –40 dB, RMS ³⁰
	Measurement length	entire PPDU

Center frequency error		
Frequency measurement uncertainty	IEEE 802.11n (2.4 GHz band), for ≥ 100 symbol (400 μs)	< 20 Hz + drift of timebase, see general technical specifications
	IEEE 802.11n (5 GHz band), for ≥ 100 symbol (400 μs)	< 35 Hz + drift of timebase, see general technical specifications

Symbol clock error		
Uncertainty		< 1 ppm

I/Q offset		
Inherent I/Q offset	for average ≥ 10 measurements	< –45 dB

Spectrum flatness		
Level uncertainty	IEEE 802.11n (2.4 GHz band) bandwidth 20 MHz	< 0.5 dB
	bandwidth 40 MHz	< 0.8 dB
	IEEE 802.11n (5 GHz band) bandwidth 20 MHz	< 0.8 dB
	bandwidth 40 MHz	< 1.0 dB

Spectrum measurements

Transmit spectrum mask		
Frequency span		up to 160 MHz
Dynamic range		in line with IEEE 802.11n
Expected nominal power setting for full dynamic range	RF1 COM, RF2 COM	
	IEEE 802.11n (2.4 GHz band)	+2 dBm to +42 dBm ²⁹
	IEEE 802.11n (5 GHz band)	+12 dBm to +42 dBm ²⁹

²⁸ Measured with channel estimation based on payload.

²⁹ The maximum permissible continuous power is +34 dBm due to thermal limits.

³⁰ 3 dB less with R&S[®]CMW-H590D RF frontend (ADV.).

WLAN N MISO RF analyzer (R&S®CMW-KM652 option)

Frequency range	WLAN IEEE 802.11n (2.4 GHz band)	2412 MHz to 2484 MHz
	WLAN IEEE 802.11n (5 GHz band), prerequisite: R&S®CMW-KB036 option	5000 MHz to 6000 MHz, for frequency exceptions for inherent spurious response, see general technical specifications
Statistics		
Statistical count		1 to 1000
Values		current, average, maximum, standard deviation
Trigger		
Trigger sources		WLAN: IF power
High throughput		
PPDU format		mixed mode, greenfield mode

Modulation analysis

Bandwidth		20 MHz, 40MHz
Level range		-28 dBm to +42 dBm ³¹
Payload length		≥ 16 symbol (max. 1024)
Analysis modes ³²		MCS0 to MCS7: data and pilot, MCS8 to MCS31: pilot only, MCS33 to MCS76: pilot only
Measured parameters	numeric results and standard deviation	total power, STS1 to STS4 power, EVM all carriers, EVM data carriers, EVM pilot carriers, center frequency error
Error vector magnitude (EVM)		
Inherent EVM ³³	IEEE 802.11n (2.4 GHz band)	
	-28 dBm ≤ input level ≤ +42 dBm ³¹ , RMS	< -40 dB, RMS ³⁴
	IEEE 802.11n (5 GHz band)	
	-18 dBm ≤ input level ≤ +42 dBm ³¹ , RMS	< -40 dB, RMS ³⁴
Measurement length		entire PPDU
Center frequency error		
Frequency measurement uncertainty	IEEE 802.11n (2.4 GHz band), for ≥ 100 symbol (400 μs)	< 20 Hz + drift of timebase, see general technical specifications
	IEEE 802.11n (5 GHz band), for ≥ 100 symbol (400 μs)	< 35 Hz + drift of timebase, see general technical specifications

³¹ The maximum permissible continuous power is +34 dBm due to thermal limits.

³² Modulation analysis on data possible after initial acquisition of training data.

³³ Measured with channel estimation based on payload.

³⁴ 3 dB less with R&S®CMW-H590D RF frontend (ADV.).

WLAN N switched MIMO RF analyzer (R&S®CMW-KM653 option)

Frequency range	WLAN IEEE 802.11n (2.4 GHz band)	2412 MHz to 2484 MHz
	WLAN IEEE 802.11n (5 GHz band), prerequisite: R&S®CMW-KB036 option	5000 MHz to 6000 MHz, for frequency exceptions for inherent spurious response, see general technical specifications
Statistics		
Statistical count		1 to 1000
Values		current, average, maximum, standard deviation
Trigger		
Trigger sources		WLAN: IF power
High throughput (HT)		
PPDU format		mixed mode, greenfield mode

Modulation analysis

Bandwidth		20 MHz, 40 MHz
Level range		-28 dBm to +42 dBm ³⁵
Payload length		≥ 16 symbol
Analysis modes		BPSK code rate 1/2 (MCS0), BPSK code rate 3/4, QPSK code rate 1/2 (MCS1), QPSK code rate 3/4 (MCS2), 16QAM code rate 1/2 (MCS3), 16QAM code rate 3/4 (MCS4), 64QAM code rate 1/2, 64QAM code rate 2/3 (MCS5), 64QAM code rate 3/4 (MCS6), 64QAM code rate 5/6 (MCS7)
	for optional 40 MHz MCS format	BPSK code rate 1/2 (MCS32)
Measured parameters	numeric results and standard deviation	total power, EVM all carriers, EVM data carriers, EVM pilot carriers, center frequency error, symbol clock error,
	numeric results for each spatial stream	EVM all carriers, EVM data carriers, EVM pilot carriers power I/Q offset

WLAN P RF analyzer (R&S®CMW-KM655 option)

Frequency range	WLAN IEEE 802.11p, prerequisite: R&S®CMW-KB036 option	5000 MHz to 6000 MHz, for frequency exceptions for inherent spurious response, see general technical specifications
Statistics		
Statistical count		1 to 1000
Values		current, average, maximum, standard deviation
Trigger		
Trigger sources		WLAN: IF power

³⁵ The maximum permissible continuous power is +34 dBm due to thermal limits.

Modulation analysis

Filter		5 MHz, 10 MHz, 20 MHz
Level range		-28 dBm to +42 dBm ³⁶
Payload length		≥ 16 symbol
Analysis modes	OFDM 5 MHz channel spacing	1.5 Mbps BPSK, 2.25 Mbps BPSK, 3 Mbps QPSK, 4.5 Mbps QPSK, 6 Mbps 16QAM, 9 Mbps 16QAM, 12 Mbps 64QAM, 13.5 Mbps 64QAM
	OFDM 10 MHz channel spacing	3 Mbps BPSK, 4.5 Mbps BPSK, 6 Mbps QPSK, 9 Mbps QPSK, 12 Mbps 16QAM, 18 Mbps 16QAM, 24 Mbps 64QAM, 27 Mbps 64QAM
	OFDM 20 MHz channel spacing	6 Mbps BPSK, 9 Mbps BPSK, 12 Mbps QPSK, 18 Mbps QPSK, 24 Mbps 16QAM, 36 Mbps 16QAM, 48 Mbps 64QAM, 54 Mbps 64QAM
Measured parameters	OFDM, numeric results and standard deviation	burst power, EVM all carriers, EVM data carriers, EVM pilot carriers, center frequency error, symbol clock error, I/Q offset, gain imbalance, quadrature error
	OFDM, graphical	EVM versus symbol, EVM versus carrier, I/Q constellation, spectrum flatness
Error vector magnitude (EVM)		
Inherent EVM ³⁷	-18 dBm ≤ input level ≤ +42 dBm ³⁶ , RMS	< -40 dB, RMS ³⁸
Measurement length		entire PPDU
Center frequency error		
Frequency measurement uncertainty	for ≥ 100 symbol (400 μs)	< 35 Hz + drift of timebase, see general technical specifications
Symbol clock error		
Uncertainty		< 1 ppm
I/Q offset		
Inherent I/Q offset	for average ≥ 10 measurements	< -45 dB
Spectrum flatness		
Level uncertainty		< 0.8 dB

³⁶ The maximum permissible continuous power is +34 dBm due to thermal limits.

³⁷ Measured with channel estimation based on payload.

³⁸ 3 dB less with R&S®CMW-H590D RF frontend (ADV.).

Spectrum measurements

Transmit spectrum mask		
Frequency span		up to 80 MHz
Dynamic range		in line with IEEE 802.11p up to class B
Expected nominal power setting for full dynamic range	RF1 COM, RF2 COM	+12 dBm to +42 dBm ³⁹

WLAN AC RF analyzer (R&S® CMW-KM656 option)

Frequency range	WLAN IEEE 802.11ac (5 GHz band), prerequisite: R&S®CMW-KB036 option	5000 MHz to 6000 MHz, for frequency exceptions for inherent spurious response, see general technical specifications
------------------------	---	---

Statistics		
Statistical count		1 to 1000
Values		current, average, maximum, standard deviation

Trigger		
Trigger sources		WLAN: IF power

High throughput (HT)		
PPDU format		mixed mode

Modulation analysis

Bandwidth		20 MHz, 40 MHz, 80 MHz, 160 MHz
Level range		-28 dBm to +42 dBm ³⁹
Payload length		≥ 1 symbol
Analysis modes		BPSK code rate 1/2 (MCS0), BPSK code rate 3/4, QPSK code rate 1/2 (MCS1), QPSK code rate 3/4 (MCS2), 16QAM code rate 1/2 (MCS3), 16QAM code rate 3/4 (MCS4), 64QAM code rate 1/2, 64QAM code rate 2/3 (MCS5), 64QAM code rate 3/4 (MCS6), 64QAM code rate 5/6 (MCS7) 256QAM code rate 3/4 (MCS8) 256QAM code rate 5/6 (MCS9)

Measured parameters	numeric results and standard deviation	burst power, EVM all carriers, EVM data carriers, EVM pilot carriers, center frequency error, symbol clock error, I/Q offset
	graphical	EVM versus symbol, spectrum flatness, I/Q constellation, transmit spectrum mask

Error vector magnitude (EVM)		
Inherent EVM ⁴⁰	bandwidth 20 MHz, 40 MHz, 80 MHz	
	-18 dBm ≤ input level ≤ +42 dBm ³⁹ , RMS	< -38 dB, RMS ⁴¹
	bandwidth 160 MHz	
	-15 dBm ≤ input level ≤ +42 dBm ³⁹ , RMS	typ. < -38 dB, RMS ⁴¹

³⁹ The maximum permissible continuous power is +34 dBm due to thermal limits.⁴⁰ Measured with channel estimation based on payload.⁴¹ 3 dB less with R&S®CMW-H590D RF frontend (ADV.).

Measurement length		entire PPDU
Center frequency error		
Frequency measurement uncertainty	for ≥ 100 symbol (400 μ s)	< 35 Hz + drift of timebase, see general technical specifications
Symbol clock error		
Uncertainty	for ≥ 100 symbol (400 μ s)	< 1 ppm
I/Q offset		
Inherent I/Q offset	for average ≥ 10 measurements	< -45 dB
Spectrum flatness		
Level uncertainty	bandwidth 20 MHz	< 0.8 dB
	bandwidth 40 MHz	< 1.0 dB
	bandwidth 80 MHz	< 1.5 dB
	bandwidth 160 MHz	typ. < 1.5 dB

Spectrum measurements

Transmit spectrum mask		
Frequency span		up to 640 MHz
Dynamic range		in line with IEEE 802.11ac
Expected nominal power setting for full dynamic range	RF1 COM, RF2 COM	+12 dBm to +42 dBm ⁴²

WLAN signaling access point emulator ⁴³ (prerequisite: R&S[®] CMW-KS650, R&S[®] CMW-KS651, R&S[®] CMW-B200A, R&S[®] CMW-B270A options)

Standard		IEEE 802.11a, g (OFDM), n
Physical layer mode		OFDM
Frequency range	WLAN IEEE 802.11n (2.4 GHz band), WLAN IEEE 802.11g (OFDM), (2.4 GHz band)	2412 MHz to 2484 MHz
	WLAN IEEE 802.11a (5 GHz band), WLAN IEEE 802.11n (5 GHz band), prerequisite: R&S [®] CMW-KB036 option	5180 MHz to 5825 MHz
Output level range RF1 COM, RF2 COM	2.4 GHz band	burst power (RMS) up to -16 dBm
	5 GHz band	burst power (RMS) up to -26 dBm burst power (RMS) up to -16 dBm (overranging)
RF1 OUT	2.4 GHz band	burst power (RMS) up to -3 dBm
	5 GHz band	burst power (RMS) up to -13 dBm burst power (RMS) up to -3 dBm (overranging)
Output level uncertainty		see general technical specifications
Output level resolution		see general technical specifications
Modulation accuracy (EVM)	2.4 GHz band	< -38 dB
	5 GHz band	< -38 dB
Minimum input level	RF1 COM, RF2 COM	down to -40 dBm

⁴² The maximum permissible continuous power is +34 dBm due to thermal limits.

⁴³ R&S[®]CMW500 and R&S[®]CMW270 only.

Physical layer OFDM

FFT size		64
Bandwidth		20 MHz
Cyclic prefix		800 ns
Physical layer mode		SISO
Modulation	IEEE 802.11a, g (OFDM)	BPSK, QPSK, 16QAM, 64QAM (bit rate: 6/9/12/18/24/36/48/54 Mbps)
	IEEE 802.11n	MCS 0 to 7
Channel coding		BCC

Measurements

PER		
Measurement range	graphically displayed, stop on limit fail	0 % to 100 %
Payload mode		data interval, payload size
Acknowledge type		ACK
Data	DL	All 0, All 1, bit pattern: 0101, bit pattern: 1010, pseudo random, PN9 to PN32
Mobile capabilities		MAC address, MAC version

Features

Connection status	status indication	signal on, associated, authenticated, probed, deauthenticated
Trigger output	WLAN signaling: frame trigger	adjustable pulse width, invertible
	WLAN signaling: RX trigger	invertible

WiMAX™ specifications – mobile station and base station test

Standard	IEEE 802.16e-2005, OFDMA
----------	--------------------------

WiMAX™ RF generator (prerequisite: R&S® CMW-B110A/R&S® CMW-B110D option)

Frequency range	WiMAX™ band 1	2300 MHz to 2800 MHz
	WiMAX™ band 2, prerequisite: R&S® CMW-KB036 option	3300 MHz to 3800 MHz
	WiMAX™ band 3, prerequisite: R&S® CMW-KB036 option	5100 MHz to 5850 MHz

WiMAX™ WinIQSIM2™ (R&S® CMW-KW700 option)

Arbitrary waveform file	in line with IEEE 802.16e-2005, OFDMA average power	WIMAX_DL_3-BURST_46_5MS.WV (PAR = 11.11 dB)
-------------------------	--	--

Output level range	depending on PAR	see general technical specifications
Output level uncertainty	waveform file used: WIMAX_DL_3-BURST_46_5MS.WV	see general technical specifications
Output level resolution		see general technical specifications

Signal quality		
Error vector magnitude (EVM)	ID_Cell = 0, permbase = 0, prbs_id = 0, cp = 1/8, BW = 10 MHz, bursts: FCH, DL-MAP, data PN15, modulation type and coding rate QPSK 1/2; waveform file used: WIMAX_DL_3BURST_46_5MS.WV	< -40 dB, RMS

WiMAX™ RF analyzer (R&S® CMW-KM700, R&S® CMW-KM701 options)

FFT size		512, 1024
Bandwidth		3.5 MHz, 5 MHz, 7 MHz, 8.75 MHz, 10 MHz
Link direction		uplink, downlink
Subcarrier allocation		DL PUSC, UL PUSC, uplink collaborative MIMO

Frequency range	WiMAX™ band 1	2300 MHz to 2800 MHz
	WiMAX™ band 2, prerequisite: R&S® CMW-KB036 option	3300 MHz to 3800 MHz
	WiMAX™ band 3, prerequisite: R&S® CMW-KB036 option	5100 MHz to 5850 MHz, for frequency exceptions for inherent spurious response, see general technical specifications
Level setting		manual mode
Level range	RF1 COM, RF2 COM	-40 dBm to +27 dBm, RMS

Statistics		
Statistical count		1 to 1000
Values		current, average, minimum, maximum

Trigger		
Trigger source		BASE: external TRIG A, BASE: external TRIG B, GPRF: BB generator, WiMAX™: IF power, WiMAX™ signaling: frame trigger

Measured parameters	numeric results	RMS power (subframe, burst, preamble), subcarrier power, crest factor, error vector magnitude (all carriers, pilot carriers, data carriers), unmodulated EVM, frequency error, sample clock error, I/Q DC offset, I/Q imbalance gain, I/Q imbalance quadrature, RSSI, CINR, spectrum flatness, spectrum flatness, neighbor, occupied bandwidth, spectrum emission mask, adjacent channel power
	graphical with the R&S®CMW-KM700 option	power versus time, constellation diagram
	graphical with the R&S®CMW-KM700 and R&S®CMW-KM701 options	FFT, spectral flatness, spectral flatness, neighbor, spectrum emission mask, adjacent channel power, CCDF, EVM versus carrier, EVM versus symbol

Power measurement

Power	RMS detector	
Level uncertainty		see general technical specifications ⁴⁴

Modulation analysis

Error vector magnitude		
Measurement range		from inherent EVM up to -12 dB
Inherent EVM ⁴⁴	WiMAX™ band 1 UL	
	-15 dBm ≤ input level ≤ +27 dBm	< -40 dB, RMS
	-35 dBm ≤ input level < -15 dBm	< -36 dB, RMS
	WiMAX™ band 2 UL	
	-15 dBm ≤ input level ≤ +27 dBm	< -38 dB, RMS
	-35 dBm ≤ input level < -15 dBm	< -35 dB, RMS
	WiMAX™ band 3 UL	
	-15 dBm ≤ input level ≤ +27 dBm	< -38 dB, RMS
	-35 dBm ≤ input level < -15 dBm	< -35 dB, RMS
	WiMAX™ band 1 DL	
	-18 dBm ≤ input level ≤ +27 dBm	< -38 dB, RMS
	WiMAX™ band 2 DL	
	-18 dBm ≤ input level ≤ +27 dBm	< -36 dB, RMS
	WiMAX™ band 3 DL	
-18 dBm ≤ input level ≤ +27 dBm	< -36 dB, RMS	

Frequency error		
Measurement range	FFT size 512, BW = 3.5 MHz	-27.34 kHz to +27.34 kHz
	FFT size 512, BW = 5 MHz	-38.28 kHz to +38.28 kHz
	FFT size 1024, BW = 7 MHz	-27.34 kHz to +27.34 kHz
	FFT size 1024, BW = 8.75 MHz	-34.18 kHz to +34.18 kHz
	FFT size 1024, BW = 10 MHz	-38.28 kHz to +38.28 kHz
Frequency measurement uncertainty		< 10 Hz + drift of timebase, see general technical specifications ⁴⁴

⁴⁴ Averaging across 100 bursts, UL: BW = 10 MHz, zone length = 18 symbols / 210 slots; DL: BW = 10 MHz, zone length = 34 symbols / 30 subchannels, channel estimation = payload.

Sample clock error ⁴⁵		
Measurement range		-5 ppm to +5 ppm
Sample clock measurement uncertainty		< 0.1 ppm
I/Q imbalance ⁴⁵		
Inherent I/Q gain imbalance		< 0.1 dB
Inherent I/Q quadrature imbalance		< 0.1°
Spectrum flatness, neighbor ⁴⁵		
Level uncertainty	inner carriers/outer carriers	< 0.5 dB
	neighbor subcarriers	< 0.1 dB

Spectrum measurements

Adjacent channel power	RMS detector	
Filter		rectangle 5 MHz, 10 MHz 3.84 MHz or 7.68 MHz, RRC, $\alpha = 0.22$, WCDMA
Dynamic range	adjacent channels	> 45 dB
Expected nominal power setting for full dynamic range	RF1 COM, RF2 COM	> -3 dBm

Spectrum emission mask (SEM)	RMS detector	
Frequency span		60 MHz
Supported masks		IEEE, WiMAX Forum [®] , TTA, user-defined
Dynamic range	relative limit of IEEE mask	> 50 dB
Expected nominal power setting for full dynamic range	RF1 COM, RF2 COM	> -3 dBm

WiMAX™ signaling base station emulator⁴⁶ (SISO prerequisite: R&S[®]CMW-KS700, R&S[®]CMW-B200A, R&S[®]CMW-B270A options, MIMO prerequisite: R&S[®]CMW-KS700, R&S[®]CMW-KS701, R&S[®]CMW-KS702, R&S[®]CMW-B200A, R&S[®]CMW-B270A options)

Standard		IEEE 802.16e
Physical layer mode		OFDMA

Frequency range		
WiMAX™ band 1, WiMAX™ band 2, WiMAX™ band 3	DL UL	see WiMAX™ RF generator specifications see WiMAX™ RF analyzer specifications

Output level range		
RF1 COM, RF2 COM, RF1 OUT	peak envelope power (PEP)	see general technical specifications
	preamble power	up to -17.7 dBm ⁴⁷ offset to peak envelope power
	single data subcarrier power	up to -51.2 dBm ⁴⁷ offset to peak envelope power
Output level uncertainty		see general technical specifications
Output level resolution		see general technical specifications
Output level setting		manual mode
Output level reference	DL	single data subcarrier power

⁴⁵ Averaging across 100 bursts, UL: BW = 10 MHz, zone length = 18 symbols / 210 slots; DL: BW = 10 MHz, zone length = 34 symbols / 30 subchannels, channel estimation = payload.

⁴⁶ R&S[®]CMW500 and R&S[®]CMW270 only.

⁴⁷ BW = 10 MHz, all subchannels used.

Physical layer

FFT size		512, 1024
Bandwidth		3.5 MHz, 5 MHz, 7 MHz, 8.75 MHz, 10 MHz
Duplexing		TDD mode
Frame duration		5 ms
Cyclic prefix		1/8
Number of OFDMA symbols		26 to 35
Link mode		SISO, MIMO – Matrix A, MIMO – Matrix B, MIMO – collaborative pattern A, MIMO – collaborative pattern B
Zone	DL	first zone, second zone
	UL	first zone, second zone
Segmentation	DL	first zone
Subcarrier allocation		first zone: PUSC second DL zone: PUSC, FUSC, AMC 2x3 second UL zone: PUSC, AMC 2x3
Modulation	FEC code type: DL	QPSK 1/2, QPSK 3/4, 16QAM 1/2, 16QAM 3/4, 64QAM 1/2, 64QAM 2/3, 64QAM 3/4, 64QAM 5/6
	FEC code type: UL	QPSK 1/2, QPSK 3/4, 16QAM 1/2, 16QAM 3/4, 64QAM 5/6
Channel coding		convolutional (CC), turbo (CTC)

Measurements

PER		
Measurement range	graphically displayed, stop on limit fail	0 % to 100 %
Payload mode	auto mode and user-defined mode	region, data interval, payload size
Acknowledge type		ARQ, HARQ, ping
Number of HARQ subbursts	HARQ, ARQ in HARQ, ICMP in HARQ	2
Data	DL	All 0, All 1, bit pattern: 0101, bit pattern: 1010, pseudo random, PN9 to PN23
Estimated BER		ARQ, HARQ, ping
Physical parameters	graphically displayed	power, frequency offset, timing offset
Mobile capabilities		MAC address, DL service flows, UL service flows, time adjustment, carrier frequency error max. TX power, carrier permutation support summary, ARQ type support summary, mobility feature support summary
Measurement reports	reported from DUT	RSSI, CINR (mean and SD), TX power
CQICH		physical and effective CINR

Features

Connection status	status indication	signal on, network entry completed, waiting for CDMA RNG-RSP, waiting for initial RNG-RSP, waiting for SBC-RSP, waiting for REG-RSP, deregistered, MS disconnected
MS capability tests		sleep mode, idle mode, cell reselection, handover
Cell reselection		MS/BS scan initiation, neighbor cell configuration for advertisement
Handover test		MS/BS initiation, neighbor cell configuration
Ranging control		initial ranging, periodic ranging
Power control		open loop, closed loop
Power boosting		preamble, pilots, FCH, DL map, UL map, data and management bursts
Burst allocation mode	data burst region	optimized, normal
Bandwidth allocation mode	data burst region	dynamic, fixed
Dummy burst generator	unused symbols filled with	pilots, dummy burst
Sample frequency offset		-1000 Hz to +1000 Hz
AWGN	CN ratio	-6 dB to +40 dB, two channels
Trigger output	WiMAX™ signaling: frame trigger	adjustable offset (positive and negative), adjustable pulse width, slope
Service flows		fragmentation control, UL ACK channel configuration

WiMAX™ IP application enabler (prerequisite: R&S® CMW-KA700, R&S® CMW-B660, R&S® CMW-B661 options)

Key features		throughput measurement and end-to-end application testing
Interface	rear panel	1 GBaseT
Convergence sublayer	IP version	V4
Protocols		DHCP, RIP
DHCP support		enable, disable (static IP)
Network settings		WiMAX™ stack IP, MS IP address (destination), subnet mask, gateway, DNS server
Interface to IP-based server/client applications		e.g. IPERF (throughput test), e.g. web browsing, e.g. FTP file transfer, e.g. video streaming, e.g. VoIP
Data throughput	end-to-end IP connection	
	DL: UDP, SISO	up to 17.2 Mbps
	DL: UDP, MIMO	up to 36.5 Mbps
	UL: UDP, SISO	up to 9.7 Mbps

TD-SCDMA specifications – mobile station (UE) test ⁴⁸

Standard	TD-SCDMA CWTS
----------	---------------

TD-SCDMA RF generator (prerequisite: R&S[®]CMW-B110A/R&S[®]CMW-B110D option)

Frequency range ⁴⁹	TD-SCDMA band A channels 10054 to 10121	2010.8 MHz to 2024.2 MHz
	TD-SCDMA band E channels 11504 to 11996	2300.8 MHz to 2399.2 MHz
	TD-SCDMA band F channels 9404 to 9596	1880.8 MHz to 1919.2 MHz

TD-SCDMA WinIQSIM2™ (R&S[®]CMW-KW750 option) and TD-SCDMA ENH. WinIQSIM2™ (R&S[®]CMW-KW751 option)

Arbitrary waveform files	with the R&S [®] CMW-KW750 option	TD-SCDMA_DEFAULT.WV (PAR = 3.14 dB), TD-SCDMA_PTWLOW.WV (PAR = 2.67 dB)
	with the R&S [®] CMW-KW750 and R&S [®] CMW-KW751 options	TD-SCDMA-DL_12K2.WV (PAR = 5.41 dB)

Output level range	depending on PAR	see general technical specifications
Output level uncertainty	waveform file used: TD-SCDMA_PTWLOW.WV	see general technical specifications
Output level resolution		see general technical specifications

Signal quality		
Error vector magnitude (EVM)	composite EVM, waveform file used: TD-SCDMA_DEFAULT.WV	< 4 %, RMS

TD-SCDMA RF analyzer (R&S[®]CMW-KM750 option)

Frequency range ⁴⁹	TD-SCDMA band A channels 10054 to 10121	2010.8 MHz to 2024.2 MHz
	TD-SCDMA band E channels 11504 to 11996	2300.8 MHz to 2399.2 MHz
	TD-SCDMA band F channels 9404 to 9596	1880.8 MHz to 1919.2 MHz

Statistics		
Statistical count		1 to 1000
Values		current, average, minimum/maximum, standard deviation

Trigger		
Trigger sources		BASE: external TRIG A, BASE: external TRIG B, GPRF: BB generator, TD-SCDMA: free run, TD-SCDMA: IF power

⁴⁸ R&S[®]CMW500 and R&S[®]CMW280 only.

⁴⁹ Bands A, E, F in line with the CCSA standard.

Modulation analysis

Filter		1.28 MHz, RRC, $\alpha = 0.22$, TD-SCDMA filter
Level range		-28 dBm to +42 dBm ⁵⁰
Analysis modes	TD-SCDMA uplink	QPSK, DPCH, QPSK, DPCH + HSDPA, 16QAM, DPCH + HSUPA
Measured parameters	numeric results and standard deviation	error vector magnitude (EVM), magnitude error (ME), phase error (PE), frequency error, I/Q origin offset, I/Q imbalance, UE power
	graphical	EVM versus time, ME versus time, PE versus time

Error vector magnitude (EVM)		
Measurement range		up to 25 %, RMS
Inherent EVM		< 2.5 %, RMS
Measurement length		1 slot, multislot (1 to 112)

Frequency error		
Measurement range		± 3 kHz
Frequency measurement uncertainty		< 20 Hz + drift of timebase, see general technical specifications

I/Q origin offset		
Inherent I/Q offset	for average ≥ 10 measurements	< -55 dB

I/Q imbalance		
Inherent I/Q imbalance		< -50 dB

Code domain

Filter		1.28 MHz, RRC, $\alpha = 0.22$, TD-SCDMA filter
Level range		-28 dBm to +42 dBm ⁵⁰
Analysis modes	TD-SCDMA uplink	QPSK, DPCH, QPSK, DPCH + HSDPA, 16QAM, DPCH + HSUPA
Measured parameters	numeric results and standard deviation	code domain error (CDE)
	graphical	code domain power versus code

Code domain power versus code		
Uncertainty		< 0.4 dB
Measurement length		1 slot

Code domain error (CDE)		
Uncertainty		< 0.4 dB
Measurement length		1 slot

Spectrum measurements

Adjacent channel leakage ratio	RMS detector	
Filter		1.28 MHz, RRC, $\alpha = 0.22$, TD-SCDMA filter
Dynamic range	first adjacent channel at ± 1.6 MHz	> 53 dB
	second adjacent channel at ± 3.2 MHz	> 61 dB
Expected nominal power setting for full dynamic range	RF1 COM, RF2 COM	-3 dBm to +42 dBm ⁵⁰

⁵⁰ The maximum permissible continuous power is +34 dBm due to thermal limits.

Uncertainty	for –33 dBc first adjacent channel level	< 0.5 dB
	for –43 dBc second adjacent channel level	< 0.5 dB
Measurement length		1 slot

Power meter

Measured parameters	numeric current RMS values	UE power
UE power	RMS detector	
Filter		bandpass, 2.1 MHz, RRC, $\alpha = 0.22$
Level range		–55 dBm to +42 dBm ⁵¹
Level uncertainty		see general technical specifications
Measurement length		1 slot

TD-SCDMA signaling (prerequisite: R&S®CMW-KS750, R&S®CMW-B300A/R&S®CMW-B300B options)

Standard		3GPP TDD
Symbol rate		1.28 MHz

Channels		
Physical channels	DL	P-CCPCH, S-CCPCH, DwPCH, FPACH, PICH, DPCH
	UL	UpPCH, PRACH, DPCH
Radio bearer	DPCH signaling radio bearer (SRB)	
	DL	2.5 kbps, 3.4 kbps
	UL	2.5 kbps, 3.4 kbps
	DPCH reference measurement channels (RMC) in line with 3GPP TS 34.122	
	DL	12.2 kbps
	UL	12.2 kbps
	DPCH voice echo	12.2 kbps
	DPCH voice echo NB-AMR	4.75 kbps, 5.15 kbps, 5.9 kbps, 6.7 kbps, 7.4 kbps, 7.95 kbps 10.2 kbps, 12.2 kbps
	DPCH video echo	64 kbps

Frequency range		
Bands A, E, F	with the R&S®CMW-KS750 option	
	DL	see TD-SCDMA RF generator specifications
	UL	see TD-SCDMA RF analyzer specifications

Frequency setting		channel number
--------------------------	--	----------------

Output level range	P-CCPCH, depending on PAR	see general technical specifications
Output level uncertainty	P-CCPCH	see general technical specifications
Output level resolution	P-CCPCH	see general technical specifications
Output level setting	P-CCPCH	total output power

Channel levels	S-CCPCH, DwPCH, FPACH, PICH, DPCH	–30 dB to +0 dB relative to total power
-----------------------	-----------------------------------	---

Signal quality		
Error vector magnitude (EVM)	global EVM for DL RMC in line with 3GPP TS 34.122 C3.1 to C3.4	< 2 %, RMS

⁵¹ The maximum permissible continuous power is +34 dBm due to thermal limits.

CDMA2000[®] 1xRTT specifications – mobile station test ⁵²

Standard	CDMA2000 [®] standards	TIA/EIA IS-2000 Rev. 0
	CDMA2000 [®] test standards	TIA/EIA IS-98-F
Symbol rate		1.2288 Mcps

CDMA2000[®] 1xRTT RF generator (prerequisite: R&S[®] CMW-B110A/R&S[®] CMW-B110D option)

Frequency range	band class 0	860.025 MHz to 893.985 MHz
	band class 1	1930.000 MHz to 1990.000 MHz
	band class 2	917.0125 MHz to 959.9875 MHz
	band class 3	832.0125 MHz to 869.9875 MHz
	band class 4	1840.000 MHz to 1870.000 MHz
	band class 5	421.675 MHz to 493.480 MHz
	band class 6	2110.000 MHz to 2169.950 MHz
	band class 7	746.000 MHz to 764.000 MHz
	band class 8	1805.000 MHz to 1879.950 MHz
	band class 9	925.000 MHz to 958.750 MHz
	band class 10	851.000 MHz to 939.975 MHz
	band class 11	421.675 MHz to 493.475 MHz
	band class 12	915.0125 MHz to 920.9875 MHz
	band class 13	2620.000 MHz to 2690 MHz
	band class 14	1930.000 MHz to 1995.000 MHz
	band class 15	2110.000 MHz to 2155.000 MHz
	band class 16	2624.000 MHz to 2690.000 MHz
	band class 17	2624.000 MHz to 2690.000 MHz
	band class 18	757.000 MHz to 769.000 MHz
band class 19	728.000 MHz to 746.000 MHz	

CDMA2000[®] GEN (R&S[®] CMW-KG800 option)

Output level range	depending on PAR	see general technical specifications
Output level uncertainty		see general technical specifications
Output level resolution		see general technical specifications
Signal quality		
Waveform quality (rho)		> 0.99

CDMA2000[®] WinIQSIM2[™] (R&S[®] CMW-KW800 option)

Arbitrary waveform files		CDMA_OQPSK.WV (PAR = 5.54 dB) or CDMA_HPSK.WV (PAR = 6.97 dB)
Output level range	depending on PAR	see general technical specifications
Output level uncertainty	waveform file used: CDMA_OQPSK.WV or CDMA_HPSK.WV	see general technical specifications
Output level resolution		see general technical specifications
Signal quality		
Waveform quality (rho)	waveform file used: CDMA_OQPSK.WV or CDMA_HPSK.WV	> 0.99

⁵² R&S[®] CMW500 and R&S[®] CMW280 only.

CDMA2000® RF analyzer (R&S® CMW-KM800 option)

Frequency range	band class 0	815.025 MHz to 848.985 MHz
	band class 1	1850.000 MHz to 1910.000 MHz
	band class 2	872.0125 MHz to 914.9875 MHz
	band class 3	887.0125 MHz to 924.9875 MHz
	band class 4	1750.000 MHz to 1780.000 MHz
	band class 5	411.675 MHz to 483.480 MHz
	band class 6	1920.000 MHz to 1979.950 MHz
	band class 7	776.000 MHz to 794.000 MHz
	band class 8	1710.000 MHz to 1784.950 MHz
	band class 9	880.000 MHz to 913.750 MHz
	band class 10	806.000 MHz to 900.975 MHz
	band class 11	411.675 MHz to 483.475 MHz
	band class 12	870.0125 MHz to 875.9875 MHz
	band class 13	2500.000 MHz to 2570.000 MHz
	band class 14	1850.000 MHz to 1915.000 MHz
	band class 15	1710.000 MHz to 1755.000 MHz
	band class 16	2502.000 MHz to 2568.000 MHz
	band class 17	2502.000 MHz to 2567.950 MHz
	band class 18	787.000 MHz to 700.000 MHz
band class 19	698.000 MHz to 716.000 MHz	

Statistics		
Statistical count		1 to 1000
Values		current, average, minimum/maximum, standard deviation

Trigger		
Trigger sources		BASE: external TRIG A, BASE: external TRIG B, GPRF: BB generator, C2K: free run, CDMA2000® signaling: superframe (80 ms)

Modulation analysis

Filter		1.23 MHz, RRC, $\alpha = 0.22$, CDMA filter
Level range		-28 dBm to +42 dBm ⁵³
Analysis modes		OQPSK, HPSK
Measured parameters	numeric results and standard deviation	error vector magnitude (EVM), magnitude error (ME), phase error (PE), frequency error, rho, carrier feedthrough, I/Q imbalance, power, wideband power (8 MHz), narrowband power (1.23 MHz)
	graphical	EVM versus time, ME versus time, PE versus time

Waveform quality (rho)		
Uncertainty	for rho 0.9 to 1	< 0.003
Measurement length		616 chip (0.5 ms)

Error vector magnitude (EVM)		
Measurement range		up to 25 %, RMS
Inherent EVM		< 2.5 %, RMS
Measurement length		0.5 ms

⁵³ The maximum permissible continuous power is +34 dBm due to thermal limits.

Frequency error		
Measurement range		±3 kHz
Frequency measurement uncertainty		< 20 Hz + drift of timebase, see general technical specifications

Carrier feedthrough		
Inherent carrier feedthrough	for average ≥ 10 measurements	< -55 dB

I/Q imbalance		
Inherent I/Q imbalance		< -50 dB

Code domain

Filter		
Level range		1.23 MHz, RRC, $\alpha = 0.22$, CDMA filter -28 dBm to +42 dBm ⁵⁴
Measured parameters	numeric values of current, average, max. and min. values	code domain power (CDP), code domain error (CDE)
	graphical	code domain power versus code, code domain error versus code

Code domain power versus code		
Uncertainty		< 0.4 dB
Measurement length		616 chip (0.5 ms)

Code domain error versus code		
Measurement uncertainty		< 0.4 dB
Measurement length		616 chip (0.5 ms)

Spectrum measurements

Adjacent channel power	RMS detector, at the selected frequency offsets	
Filter	Gaussian	1 kHz, 6.25 kHz, 10 kHz, 12.5 kHz, 25 kHz, 30 kHz, 50 kHz
	Nyquist	100 kHz, 1 MHz, 1.23 MHz
Frequency offset interval	up to 20 adjacent channels on each side	-4 MHz to +4 MHz
Dynamic range		> 70 dB
Expected nominal power setting for full dynamic range	RF1 COM, RF2 COM	+1 dBm to +42 dBm ⁵⁴
Uncertainty	for -43 dBc adjacent channel level	< 0.5 dB
Measurement length	one power control group	1536 chip (1.25 ms)

Power meter

MS power		
Filter	narrowband	bandpass, 1.25 MHz
Filter	wideband	bandpass, 8 MHz
Level range		-55 dBm to +42 dBm ⁵⁴
Level uncertainty		see general technical specifications
Measurement length		616 chip (0.5 ms)

⁵⁴ The maximum permissible continuous power is +34 dBm due to thermal limits.

CDMA2000® 1xRTT signaling (prerequisite: R&S®CMW-KS800, R&S®CMW-B200A, R&S®CMW-B220A options)

Frequency range		
Band class 0 to band class 19	DL	see CDMA2000® 1xRTT RF generator specifications
	UL	see CDMA2000® 1xRTT RF analyzer specifications
Output level range	depending on PAR	see general technical specifications
Output level uncertainty		see general technical specifications
Output level resolution		see general technical specifications
Modulation		
Dual BPSK, multiple QPSK		1.2288 Mcps
Waveform quality (rho)		> 0.99
Code channel level uncertainty	relative to the total CDMA output power PICH, PCH, FCH, SCH0	approx. 0.1 dB
	all other channels	approx. 0.25 dB
Code channel resolution		0.1 dB
Code channel level range	relative to the total CDMA output power PICH, PCH, FCH, SCH0, SYNC	-20 dB to -1 dB
Supported service options		
Loopback service options		SO 2, 9, 55
Speech service options		SO 1, 3, 17, 68, 70, 73, 0x8000
Test data service option		SO 32
Packet data service option	prerequisite: R&S®CMW-B450D	SO 33
Speech codecs	prerequisite: R&S®CMW-B400B and R&S®CMW-B405A options	
Supported standards		8k (SO 1), 8k enhanced or EVRC-A (SO 3), 13k or QCELP (SO 17), EVRC-B (SO 68), EVRC-WB (SO 70), EVRC-NW (SO 73)

CDMA2000[®] 1xEV-DO specifications – access terminal test ⁵⁵

Standard	CDMA2000 [®] 1xEV-DO standards	TIA/EIA 856-2
	CDMA2000 [®] 1xEV-DO test standards	TIA/EIA 866-A, TIA/EIA 866-B
Symbol rate		1.2288 Mcps

CDMA2000[®] 1xEV-DO RF generator (prerequisite: R&S[®] CMW-B110A/R&S[®] CMW-B110D option)

Frequency range	band class 0	860.025 MHz to 893.985 MHz
	band class 1	1930.000 MHz to 1990.000 MHz
	band class 2	917.0125 MHz to 959.9875 MHz
	band class 3	832.0125 MHz to 869.9875 MHz
	band class 4	1840.000 MHz to 1870.000 MHz
	band class 5	421.675 MHz to 493.480 MHz
	band class 6	2110.000 MHz to 2169.950 MHz
	band class 7	746.000 MHz to 764.000 MHz
	band class 8	1805.000 MHz to 1879.950 MHz
	band class 9	925.000 MHz to 958.750 MHz
	band class 10	851.000 MHz to 939.975 MHz
	band class 11	421.675 MHz to 493.475 MHz
	band class 12	915.0125 MHz to 920.9875 MHz
	band class 13	2620.000 MHz to 2690 MHz
	band class 14	1930.000 MHz to 1995.000 MHz
	band class 15	2110.000 MHz to 2155.000 MHz
	band class 16	2624.000 MHz to 2690.000 MHz
	band class 17	2624.000 MHz to 2690.000 MHz
	band class 18	757.000 MHz to 769.000 MHz
band class 19	728.000 MHz to 746.000 MHz	

1xEV-DO WinIQSIM2[™] (R&S[®] CMW-KW880 option)

Arbitrary waveform file		EVDO_DEFAULT.WV (PAR = 4.85 dB)
Output level range	depending on PAR	see general technical specifications
Output level uncertainty	waveform file used: EVDO_DEFAULT.WV	see general technical specifications
Output level resolution		see general technical specifications
Signal quality		
Waveform quality (rho)	waveform file used: EVDO_DEFAULT.WV	> 0.99

CDMA2000[®] 1xEV-DO RF analyzer (R&S[®] CMW-KM880 option)

Frequency range	band class 0	815.025 MHz to 848.985 MHz
	band class 1	1850.000 MHz to 1910.000 MHz
	band class 2	872.0125 MHz to 914.9875 MHz
	band class 3	887.0125 MHz to 924.9875 MHz
	band class 4	1750.000 MHz to 1780.000 MHz
	band class 5	411.675 MHz to 483.480 MHz
	band class 6	1920.000 MHz to 1979.950 MHz
	band class 7	776.000 MHz to 794.000 MHz
	band class 8	1710.000 MHz to 1784.950 MHz
	band class 9	880.000 MHz to 913.750 MHz
	band class 10	806.000 MHz to 900.975 MHz
	band class 11	411.675 MHz to 483.475 MHz
	band class 12	870.0125 MHz to 875.9875 MHz
	band class 13	2500.000 MHz to 2570.000 MHz
	band class 14	1850.000 MHz to 1915.000 MHz
	band class 15	1710.000 MHz to 1755.000 MHz
	band class 16	2502.000 MHz to 2568.000 MHz
	band class 17	2502.000 MHz to 2567.950 MHz
	band class 18	787.000 MHz to 700.000 MHz
band class 19	698.000 MHz to 716.000 MHz	

⁵⁵ R&S[®]CMW500 and R&S[®]CMW280 only.

Statistics		
Statistical count		1 to 1000
Values		current, average, minimum/maximum, standard deviation

Trigger		
Trigger sources		BASE: external TRIG A, BASE: external TRIG B, GPRF: BB generator, 1xEV-DO: free run, 1xEV-DO signaling: superframe (80 ms)

Modulation analysis

Filter		1.23 MHz, RRC, $\alpha = 0.22$, CDMA filter
Level range		-28 dBm to +42 dBm ⁵⁶
Analysis modes		dual BPSK
Multicarrier		single carrier or 3 carriers within -8 MHz to +8 MHz
Measured parameters	numeric results and standard deviation	error vector magnitude (EVM), magnitude error (ME), phase error (PE), frequency error, rho, carrier feedthrough, I/Q imbalance, power, wideband power (8 MHz for single carrier or 16 MHz for multicarrier), narrowband power (1.23 MHz)
	graphical	EVM versus time, ME versus time, PE versus time

Waveform quality (rho)		
Uncertainty	for rho 0.9 to 1	< 0.003
Measurement length	half-slot	1024 chip (833.33 μ s)

Error vector magnitude (EVM)		
Measurement range		up to 25 %, RMS
Inherent EVM		< 2.5 %, RMS
Measurement length	half-slot	1024 chip (833.33 μ s)

Frequency error		
Measurement range		± 3 kHz
Frequency measurement uncertainty		< 20 Hz + drift of timebase, see general technical specifications

Carrier feedthrough		
Inherent carrier feedthrough	for average ≥ 10 measurements	< -55 dB

I/Q imbalance		
Inherent I/Q imbalance		< -50 dB

⁵⁶ The maximum permissible continuous power is +34 dBm due to thermal limits.

Code domain

Filter		1.23 MHz, RRC, $\alpha = 0.22$, CDMA filter
Level range		-28 dBm to +42 dBm ⁵⁷
Measured parameters	numeric values of current, average, max. and min. values	code domain power (CDP), code domain error (CDE)
	graphical	code domain power versus code, code domain error versus code

Code domain power versus code		
Uncertainty		< 0.4 dB
Measurement length	half-slot	1024 chip (833.33 μ s)

Code domain error versus code		
Measurement uncertainty		< 0.4 dB
Measurement length	half-slot	1024 chip (833.33 μ s)

Spectrum measurements

Adjacent channel power	RMS detector, at the selected frequency offsets	
Filter	Gaussian	1 kHz, 6.25 kHz, 10 kHz, 12.5 kHz, 25 kHz, 30 kHz, 50 kHz
	Nyquist	100 kHz, 1 MHz, 1.23 MHz
Frequency offset interval	up to 20 adjacent channels on each side	-4 MHz to +4 MHz to each carrier
Dynamic range		> 70 dB
Expected nominal power setting for full dynamic range	RF1 COM, RF2 COM	+1 dBm to +42 dBm ⁵⁷
Uncertainty	for -43 dBc adjacent channel level	< 0.5 dB
Measurement length	half-slot	1024 chip (833.33 μ s)

Power meter

MS power		
Filter	narrowband	bandpass, 1.25 MHz
Filter	wideband	bandpass, 8 MHz for single carrier or 16 MHz for multicarrier
Level range		-55 dBm to +42 dBm ⁵⁷
Level uncertainty		see general technical specifications
Measurement length	half-slot	1024 chip (833.33 μ s)

CDMA2000® 1xEV-DO signaling (prerequisite: R&S® CMW-KS880, R&S® CMW-KS881, R&S® CMW-B200A, R&S® CMW-B230A options)

Frequency range		
Band class 0 to band class 19	DL	see CDMA2000® 1xEV-DO RF generator specifications
	UL	see CDMA2000® 1xEV-DO RF analyzer specifications

Output level range	depending on PAR	see general technical specifications
Output level uncertainty		see general technical specifications
Output level resolution		see general technical specifications

Modulation		
Dual BPSK		1.2288 Mcps
Waveform quality (rho)		> 0.99

Supported applications		
Test applications		FTAP/RTAP, FETAP/RETAP
	prerequisite: R&S® CMW-KS881	FMCTAP/RMCTAP
Packet applications	prerequisite: R&S® CMW-B450D	

⁵⁷ The maximum permissible continuous power is +34 dBm due to thermal limits.

Data application unit (R&S[®]CMW-B450D option) ⁵⁸

The R&S[®]CMW-B450D option provides data test capabilities and makes a Gigabit Ethernet connector available on the rear of the instrument.

Data application

IP configuration		IPv4 address configuration
		IPv6 address configuration
File transfer protocol (FTP)		FTP server
		FTP traffic generator
Hypertext transfer protocol (HTTP)		HTTP server
Domain name service (DNS)		DNS server

Enabling of IP data interface for IPV4 (R&S[®]CMW-KA100 option)

Enabling of IP data interface for IPV6 (R&S[®]CMW-KA150 option)

IP multimedia subsystem server (R&S[®]CMW-KAA20 option)

IMS server VoIMS application, SMS application		IMS registration, voice over IMS, SMS over IMS
--	--	--

Data application measurements (R&S[®]CMW-KM050 option)

Measured parameters		ping, IPerf, IP throughput, DNS requests, IP logging
IP impairments		up to 7 filter rules, delay, jitter, packet loss, packet corruption

IP analysis (R&S[®]CMW-KM051 option)

Measured parameters		TCP analysis, IP connectivity, data amount per destination/protocol, trigger per IP flow, throughput per IP flow
---------------------	--	--

LAN DAU interface

LAN DAU		Ethernet RJ-45 connector, 1000 Mbps
---------	--	-------------------------------------

⁵⁸ R&S[®]CMW500 and R&S[®]CMW270 only.

Digital I/Q 1 to 4 (R&S®CMW-B510F option) and digital I/Q 5 to 8 (R&S®CMW-B520F option) ⁵⁹

The R&S®CMW-B510F option makes the first digital I/Q interface and AUX interface and the R&S®CMW-B520F option makes the second digital I/Q interface and AUX interface available on the rear of the instrument.

Digital I/Q interface

The digital I/Q interface can be used for connecting the R&S®CMW to the digital I/Q interface of other Rohde & Schwarz instruments (e.g. R&S®AMU200A, R&S®EX-IQ-Box).

DIG I/Q IN 1/3/5/7	input	26-pin MDR connector
Level		LVDS
Clock rate in		100 MHz
Clock rate out		100 MHz
DIG I/Q OUT 2/4/6/8	output	26-pin MDR connector
Level		LVDS
Clock rate		100 MHz
Control signals	general-purpose control, for future use	
	6 signals	100 MHz
I/Q data		
Resolution	for clock rate up to 100 MHz	18 bit for I and 18 bit for Q
I/Q sample rate		
Source		internal, digital input, digital output,
Range		1.92 Msample/s to 100 Msample/s
Predefined values ⁶⁰	standard-independent WCDMA, LTE	100 Msample/s 1.92 Msample/s, 3.84 Msample/s, 7.68 Msample/s, 9.6 Msample/s, 15.36 Msample/s, 19.2 Msample/s, 30.72 Msample/s
I/Q enable/request rate		
Digital input	transfer mode 1 (enable mode)	75 MHz, 100 MHz
	transfer mode 2 (request mode)	0 Hz to 100 MHz
Digital output	transfer mode 1 (enable mode)	100 MHz
	transfer mode 2 (request mode)	0 Hz to 100 MHz

AUX interface

The AUX interface can be used for connecting the R&S®CMW to other instruments, e.g. to trigger, clock and enable signals.

AUX A/B/C/D	bidirectional, half-duplex	BNC connectors
Level		3.3 V TTL
Clock rate		0 Hz to 100 MHz

Included extras

Digital I/Q cable (two sets)	same cable as included in R&S®SMU-Z6	26-pin MDR connector
-------------------------------------	--------------------------------------	----------------------

⁵⁹ R&S®CMW500 and R&S®CMW270 only.

⁶⁰ Further values in the range from 400 sample/s to 100 Msample/s can be provided on request.

General data

RF connectors (front panel)		
RF1 COM, RF2 COM		SnapN female, 50 Ω, compatible with N female connectors
RF1 OUT		combined RF input and RF output
		RF output
Remote control interfaces (front panel) ⁶¹		
LAN		Ethernet RJ-45 connector, 100 Mbps
Remote control interfaces (rear panel)		
IEEE 488	R&S®CMW-B612A IEEE bus (single) interface option	IEC 60625-2 (IEEE 488.2), 24-pin Amphenol connector
	R&S®CMW-B612B IEEE bus (dual) interface option ⁶¹	2 × IEC 60625-2 (IEEE 488.2), 24-pin Amphenol connector
LAN REMOTE		Ethernet RJ-45 connector, 1000 Mbps
USB REMOTE ⁶¹		USB 2.0 type B connector
Further interfaces (front panel)		
USB	for keyboard, mouse, USB stick	3 × USB 2.0 type A connector
SENSOR		for R&S®NRP-Zxx power sensors
DIGITAL MONITOR	for external monitor, only included in R&S®CMW-S600A or R&S®CMW-S600C or R&S®CMW-S600E configuration (front panel without display or keypad)	DVI-D connector
Further interfaces (rear panel)		
USB	for keyboard, mouse, USB stick	2 × USB 2.0 type A connector
DVI	for external monitor, R&S®CMW-B620A DVI interface option	DVI-D connector
TRIG A, TRIG B	trigger input/output output trigger sources	2 × BNC connector standard-specific internal trigger sources
Environmental conditions		
Temperature	operating temperature range storage temperature range	+5 °C to +45 °C -25 °C to +60 °C
Damp heat		in line with EN 600068-2-78, +40 °C, 80 % rel. humidity, steady state
Product conformity		
Electromagnetic compatibility	EU: in line with EMC Directive 2004/108/EC	applied harmonized standards: <ul style="list-style-type: none"> EN 61326-1 (industrial environment) EN 61326-2-1 EN 55011 (class A)
Electrical safety	EU: in line with Low Voltage Directive 2006/95/EC USA/Canada	applied harmonized standard: EN 61010-1 applied harmonized standards: <ul style="list-style-type: none"> UL 61010-1 (second edition) CAN C22.2 No. 61010.1-04
International safety approvals	VDE – Association for Electrical, Electronic and Information Technologies CSA – Canadian Standards Association	GS mark CSA _{UL} mark

⁶¹ R&S®CMW500 and R&S®CMW270 only.

Mechanical resistance	nonoperating mode	
Vibration	sinusoidal	in line with EN 60068-2-6, 5 Hz to 150 Hz, 0.15 mm amplitude const., 55 Hz to 150 Hz, 0.5 g const.
Vibration	random	in line with EN 60068-2-64, 10 Hz to 300 Hz, acceleration 1.2 g RMS
Shock		in line with MIL-STD-810E, method 516.4, procedure I, 40 g shock spectrum
Power rating		
Rated voltage		100 V to 240 V AC ($\pm 10\%$)
Rated frequency		50 Hz to 60 Hz ($\pm 5\%$)
Rated power		max. 850 VA
	standby	max. 13 W
Power consumption	R&S [®] CMW500 and R&S [®] CMW270 single tester, nonsignaling	approx. 200 W
	R&S [®] CMW280 single tester, nonsignaling	approx. 180 W
Display		selected with R&S [®] CMW-S600B or R&S [®] CMW-S600D or R&S [®] CMW-S600F configuration (front panel with display and keypad)
Size		21 cm TFT color display (8.4")
Resolution		800 × 600 pixel (SVGA resolution)
Pixel failure rate		$< 1.1 \times 10^{-5}$
Dimensions of the R&S[®]CMW500 or R&S[®]CMW270	W × H × D, overall	465.1 mm × 197.3 mm × 517.0 mm (18.31 in × 7.77 in × 20.35 in)
	for rackmounting	19" 1/1, 4 HU, 450
Dimensions of the R&S[®]CMW280	W × H × D, overall	465.1 mm × 197.3 mm × 417.0 mm (18.31 in × 7.77 in × 16.41 in)
	for rackmounting	19" 1/1, 4 HU, 350
Weight of the R&S[®]CMW500 or R&S[®]CMW270	single tester, nonsignaling	approx. 14 kg (approx. 31 lb)
	with typical options	approx. 18 kg (approx. 40 lb)
Weight of the R&S[®]CMW280	single tester, nonsignaling	approx. 12 kg (approx. 27 lb)
	with typical options	approx. 14 kg (approx. 31 lb)
Calibration interval	12 months	recommended for highest accuracy, see specified RF generator and RF analyzer level uncertainty
	24 months	add 0.2 dB to specified RF generator and RF analyzer level uncertainty

Ordering information

Designation	Type	Order No.
Wideband Radio Communication Tester Base unit with following accessories: power cord, operating manual (quick start guide), comprehensive documentation on CD-ROM	R&S®CMW500	1201.0002K50
Wireless Connectivity Tester Base unit with following accessories: power cord, operating manual (quick start guide), comprehensive documentation on CD-ROM	R&S®CMW270	1201.0002K75
Wideband Radio Communication Tester Base unit with following accessories: power cord, operating manual (quick start guide), comprehensive documentation on CD-ROM	R&S®CMW280	1201.0002K25

For more ordering information about available options, please see our product brochure (PD 5213.9211.12) or ask your local Rohde & Schwarz expert to find the solution that is optimally suited to your needs.

Recommended extras for manual operation

For R&S®CMW-S600B or R&S®CMW-S600D or R&S®CMW-S600F configuration (front panel with display and keypad):

Designation	Type	Order No.
Mouse with USB Interface, optical	R&S®PSL-Z10	1157.7060.04

For R&S®CMW-S600A or R&S®CMW-S600C or R&S®CMW-S600E configuration (front panel without display or keypad):

Designation	Type	Order No.
Mouse with USB Interface, optical	R&S®PSL-Z10	1157.7060.04
Keyboard with USB Interface (US assignment)	R&S®PSL-Z2	1157.6870.04
17" TFT Monitor	R&S®PMC3	1082.6004.12

Important information:

We recommend using only the above-mentioned original PC components from Rohde & Schwarz in connection with the R&S®CMW500, R&S®CMW270 and R&S®CMW280. The interaction of all components is continuously tested. Insufficiently shielded PC components may lead to EMC problems which may disturb RF measurements results.

Recommended extras

Designation	Type	Order No.
19" Rack Adapter	R&S®ZZA-411	1096.3283.00
Digital Signal Interface Module	R&S®EX-IQ-Box ⁶²	1409.5505K04
Cable TVR 290, 26-pin MDR connector; additional cable for R&S®CMW-B510F used with e.g. R&S®AMU200A, R&S®EX-IQ-Box	R&S®SMU-Z6 ⁶²	1415.0201.02

⁶² R&S®CMW500 and R&S®CMW270 only.

Service options

Service options		
Extended Warranty, one year	R&S®WE1	Please contact your local Rohde & Schwarz sales office.
Extended Warranty, two years	R&S®WE2	
Extended Warranty, three years	R&S®WE3	
Extended Warranty, four years	R&S®WE4	
Extended Warranty with Calibration Coverage, one year	R&S®CW1	
Extended Warranty with Calibration Coverage, two years	R&S®CW2	
Extended Warranty with Calibration Coverage, three years	R&S®CW3	
Extended Warranty with Calibration Coverage, four years	R&S®CW4	

Extended warranty with a term of one to four years (WE1 to WE4)

Repairs carried out during the contract term are free of charge⁶³. Necessary calibration and adjustments carried out during repairs are also covered. Simply contact the forwarding agent we name; your product will be picked up free of charge and returned to you in top condition a couple of days later.

Extended warranty with calibration (CW1 to CW4)

Enhance your extended warranty by adding calibration coverage at a package price. This package ensures that your Rohde & Schwarz product is regularly calibrated, inspected and maintained during the term of the contract. It includes all repairs⁶³ and calibration at the recommended intervals as well as any calibration carried out during repairs or option upgrades.

For product brochure, see PD 5213.9211.12 and www.rohde-schwarz.com

⁶³ Excluding defects caused by incorrect operation or handling and force majeure. Wear-and-tear parts are not included.

Service that adds value

- | Worldwide
- | Local and personalized
- | Customized and flexible
- | Uncompromising quality
- | Long-term dependability

About Rohde & Schwarz

Rohde & Schwarz is an independent group of companies specializing in electronics. It is a leading supplier of solutions in the fields of test and measurement, broadcasting, radiomonitoring and radiolocation, as well as secure communications. Established more than 80 years ago, Rohde & Schwarz has a global presence and a dedicated service network in over 70 countries. Company headquarters are in Munich, Germany.

Quality management and environmental management

Rohde & Schwarz is certified in line with the ISO 9001 and ISO 14001 management systems.

Certified Quality Management
ISO 9001

Certified Environmental Management
ISO 14001

Rohde & Schwarz GmbH & Co. KG

www.rohde-schwarz.com

Regional contact

- | Europe, Africa, Middle East | +49 89 4129 12345
customersupport@rohde-schwarz.com
- | North America | 1 888 TEST RSA (1 888 837 87 72)
customer.support@rsa.rohde-schwarz.com
- | Latin America | +1 410 910 79 88
customersupport.la@rohde-schwarz.com
- | Asia/Pacific | +65 65 13 04 88
customersupport.asia@rohde-schwarz.com
- | China | +86 800 810 8228/+86 400 650 5896
customersupport.china@rohde-schwarz.com

R&S® is a registered trademark of Rohde & Schwarz GmbH & Co. KG
Trade names are trademarks of the owners
PD 5213.9211.22 | Version 12.00 | January 2014 (ch)
R&S®CMW500 Wideband Radio Communication Tester
Data without tolerance limits is not binding | Subject to change
© 2007 - 2014 Rohde & Schwarz GmbH & Co. KG | 81671 München, Germany



5213921122